HICKOK

TEST DATA
MODEL 6000,6000A
6000B & 6005
TUBE TESTERS

THE HICKOK ELECTRICAL INSTRUMENT CO.
10514 DUPONT AVENUE • CLEVELAND, OHIO 44108

PHONE—(216) 541 8060 TWX—810-421-8286

PRINTED IN U.S.A.

NOTATIONS

NOTE 1: The letter that appears in the RANGE column indicates the setting of the FUNCTION SWITCH.

NOTE 2: (symbol "#" on Roll Chart) Set BIAS VOLTS at 40, press and hold down button indicated in the PRESS column while rotating BIAS VOLTS control until tube strikes. The striking voltages indicated are nominal values and reference to handbook "Critical Grid Characteristics" of Thyratron tubes reveals appreciable variations from these values.

NOTE 3: (symbol "★" on Roll Chart) Make emission tests only. Good tubes will read above index mark "RECTIFIERS & DIODES OK" on METER.

NOTE 4: Mutual Conductance Values are minimum. Discard tubes which read lower.

NOTE 5: Readjust BIAS VOLTS after button P4 is pressed, then read Gm.

NOTE 6: (symbol "🌡" on Roll Chart) A short indication on position "A" of the SHORTS switch is normal.

NOTE 7: For TUBE TESTER Models 539B and 539C, the Universal Adapter CA-5, 1050-164, is available. This Adapter provides tube test sockets for Compactrons, Novars, 5 and 7-pin Nuvistors, and the new 10-pin tubes, including Decals. Test data for these tubes is supplied in supplementary form with the Adapter. See inside back cover for description of all adapters.

NOTE 8: "Cut off" tube section NOT being tested by means of a 30 to 35 volt battery (Eveready 413, or equal). Polarity and connections are indicated in the NOTATIONS column: e. g., NOTE 8: 7-, 2+, indicates connect negative lead to pin 7 and positive lead to pin 2 of any convenient socket on the tester.

CAUTION: Disconnect battery between any change of SELECTORS.

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.		NOTATIONS
1A3	1.4	HR-0203-0	0	0	C	-----	Diode
1AD2‡	1.4	B3-0X00-0	0	42	F	-----	OK ABOVE DIODES OK
1AD4	1.1	DV-4120-0	17	62	B	1400	
1AG4	1.1	DV-4120-0	27	48	B	1000	
1AH4	1.1	FT-4120-0	17	0	B	500	
1AK4	1.1	FT-4120-0	17	0	B	500	
1AU2	1.1	EV-0900-0	0	81	F	-----	OK ABOVE DIODES OK
1AY2	1.1	CX-0X00-0	0	86	F	-----	OK ABOVE DIODES OK SET FIL. PINS ON OCTAL SOCKET PINS 2 & 7 WITH EXTERNAL LEADS
1B3	1.1	HS-0X00-0	0	80	F	-----	OK ABOVE DIODES OK
1BC2	1.1	BV-0X00-0	0	73	F	-----	
1BH2	1.1	DW-0X00-0	0	73	F	-----	CONNECT FIL. LUGS TO OCTAL SOCKET PINS 3 & 8
1BK2	1.4	BS-0X00-0	0	85	F	-----	OK ABOVE DIODES OK
1BX2	1.4	BS-0X00-0	0	80	F	-----	OK ABOVE DIODES OK
1BY2‡	1.1	B3-0X00-0	0	42	F	-----	OK ABOVE DIODES OK
1DG3	1.1	DY-0X00-0	0	42	F	-----	OK ABOVE DIODE OK
1D-K29	1.1	BS-0X00-0	0	0	D	-----	CONNECT FIL. LEADS TO PINS 1 AND 2. OK ABOVE 200 ON 3000 SCALE
1G3	1.1	HS-0X00-0	0	80	F	-----	OK ABOVE DIODES OK
1H2	1.4	BS-0X00-0	0	76	F	-----	OK ABOVE DIODES OK
1K3	1.1	HS-0X00-0	0	42	F	-----	OK ABOVE DIODES OK
1N2	1.1	HS-0X00-0	0	80	F	-----	OK ABOVE DIODES OK
1R5	1.4	BX-4306-2	55	53	A	1100	
1R-K23	1.4	ES-0X00-0	0	85	F	-----	OK ABOVE DIODES OK
1S2A	1.4	ES-0X00-0	0	85	F	-----	OK ABOVE DIODES OK
1S4	1.4	BX-3240-0	29	65	B	1500	
1S5	1.4	BX-6510-0	11	0	B	500	Pent. Sect.
1S5	1.4	BX-0300-0	0	0	C	-----	Diode Sect.
1U4	1.4	BX-6230-0	14	42	A	900	
1V2	1.1	EV-0900-0	0	78	F	-----	
1W5	1.1	EV-2780-0	11	73	B	400	OK above 250
1X2	1.1	BS-0X00-0	0	80	F	-----	OK ABOVE DIODES OK
2AF4	2.5	ET-2105-0	36	85	A	4000	
2AH2‡	2.5	B3-0X00-0	0	79	F	-----	OK ABOVE DIODES OK
2AS2‡	2.5	B3-0X00-0	0	80	F	-----	OK ABOVE DIODES OK
2AV2	2.0	EV-0900-0	0	69	F	-----	OK ABOVE DIODES OK
2AZ2	2.0	BS-0X00-0	0	88	F	-----	OK ABOVE DIODES OK
2BA2	2.0	EV-0100-0	0	90	F	-----	
2BJ2	2.5	BS-0X00-0	0	78	F	-----	OK ABOVE DIODES OK
2BN4	2.0	ET-2501-0	19	88	A	5000	
2BN4A	2.0	ET-2501-0	19	86	A	3200	
2BU2‡	2.5	B3-0X00-0	0	85	F	-----	OK ABOVE DIODES OK
2C51	6.3	KR-7608-2	16	86	A	4000	Triode No. 1
2C51	6.3	KR-3402-8	16	86	A	4000	Triode No. 2
2CN3A	2.0	HS-0X00-0	0	87	F	-----	OK ABOVE DIODES OK
2CW4‡	2.0	DR-4208-0	23	79	A	2600	USE ADAPTER SA-3, 1050-127. NOTE 3
Model 6000 A:							
2CW4	2.0	13-4208-0	23	79	A	2600	
2CY5	2.5	ET-1562-0	11	81	B	3000	
2D21	6.3	ET-1602-5	*	94	F	-----	Strikes at about 24
2DF4	2.5	EV-8310-0	21	88	A	3800	

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.		NOTATIONS
2DS4‡	2.0	DR-4208-0	22	79	A	2600	USE ADAPTER SA-3, 1050-127. NOTE 3
Model 6000 A:							
2DS4	2.0	13-4208-0	22	79	A	2600	
2DV4‡	2.0	13-6107-0	27	88	A	4600	
2DX4	2.5	ET-2105-0	29	85	A	3800	
2EA5	2.5	ET-1562-0	11	86	A	4000	
2EG4‡	2.0	DR-4208-0	22	72	A	2500	MAKE "LINE TEST" AT 1425 ON 3000 SCALE. USE ADAPTER SA-3, 1050-127 NOTE 3
Model 6000A:							
2EG4	2.0	13-4208-0	22	72	A	2500	MAKE "LINE TEST" AT 1425 ON 3000 SCALE
2EN5	2.0	ET-0705-6	0	80	C	-----	Diode No. 1
2EN5	2.0	ET-0205-6	0	80	C	-----	Diode No 2
2ER5	2.0	ET-2567-0	10	89	A	5000	
2ES5	2.5	ET-2501-0	10	87	A	4600	
2EV5	2.5	ET-1562-0	21	87	A	4000	
2FH5	2.5	ET-2507-0	14	87	A	4600	
2FQ5	2.5	ET-2507-0	19	87	A	4500	
2FQ5A	2.5	ET-2507-6	19	89	A	5200	
2FS5	2.5	ET-1567-0	10	85	A	3500	
2FV6	2.5	ET-1567-2	12	85	A	3800	
2GK5	2.5	ET-2507-6	19	89	A	5200	
2GU5	2.5	ET-1562-0	13	89	A	5500	
2GW5	2.5	ET-2105-0	20	88	A	5000	
2HA5	2.0	ET-1507-6	20	87	A	4600	
2HK5	2.5	ET-1502-0	19	88	A	5000	
2HM5	2.5	ET-1507-6	20	87	A	4000	
2HQ5	2.5	ET-1507-6	20	87	A	4400	
2T4	2.5	ET-2105-0	36	88	A	5000	
3A2	3.0	BS-0X00-0	0	85	F	-----	
3A3	3.0	HS-0X00-0	0	75	F	-----	
3AF4	3.0	ET-2105-0	36	85	A	4000	
3AL5	3.0	ET-0701-6	0	78	C	-----	Diode No. 1
3AL5	3.0	ET-0205-6	0	78	C	-----	Diode No. 2
3AT2‡	3.0	B3-0X00-0	0	84	F	-----	OK ABOVE DIODES OK
3AU6	3.0	ET-1567-2	11	76	A	2300	
3AV6	3.0	ET-1702-5	12	58	A	1250	Triode Sect.
3AV6	3.0	ET-0602-0	0	26	C	-----	Diode No. 1
3AV6	3.0	ET-0502-0	0	26	C	-----	Diode No. 2
3AW2‡	3.0	C3-0X00-0	0	87	F	-----	OK ABOVE DIODES OK
3AW3	3.0	HS-0X00-0	0	75	F	-----	
3B2	3.0	HS-0X00-0	0	70	F	-----	
3B4	2.5	EV-3710-0	50	69	A	1700	
3BA6	3.0	ET-1567-2	11	72	A	1900	
3BC5	3.0	ET-1562-0	11	78	A	2500	
3BE6	3.0	ET-7562-1	0	35	B	800	AMPL. SECT. MAKE NO GAS TEST
3BE6	3.0	ET-1602-7	20	90	A	6500	OSC. SECT. MAKE GAS TEST
3BL2‡	3.0	B3-0X00-0	0	85	F	-----	OK ABOVE DIODES OK
3BM2‡	3.0	B3-0X00-0	0	85	F	-----	OK ABOVE DIODES OK
3BN2‡	3.0	B3-0X00-0	0	68	F	-----	
3BN4	3.0	ET-2501-0	19	88	A	5000	
3BN4A	3.0	ET-2501-0	19	86	A	3200	

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.		NOTATIONS
3BN6	3.0	ET-2751-6	6	27	B	700	Limiter Grid
3BN6	3.0	ET-6751-2	13	0	B	500	Quadrature Grid
3BS2‡	3.0	B3-0X00-0	0	85	F	------	OK ABOVE DIODES OK
3BT2‡	3.0	C3-0X00-0	0	87	F	------	OK ABOVE DIODES OK
3BU8	3.0	EV-7821-9	11	30	F	------	Pent. No. 1
3BU8	3.0	EV-7321-6	11	30	F	------	Pent. No. 2
3BW2‡	3.0	B3-0X00-0	0	88	F	------	OK ABOVE DIODES OK
3BX6	3.0	EV-2781-9	10	86	A	4200	
3BY6	3.0	ET-1562-7	12	56	A	1200	Grid No. 1
3BY6	3.0	ET-7562-1	16	0	B	500	Grid No. 3
3BZ6	3.0	ET-1562-7	11	81	A	3000	
3C4	2.5	BX-6230-0	41	56	A	1200	
3CA3	3.0	HS-0X00-0	0	83	F	------	OK ABOVE DIODES OK
3CB6	3.0	ET-1562-7	11	82	A	3300	
3CE5	3.0	ET-1562-0	11	81	A	3000	
3CN3A	3.0	HS-0X00-0	0	87	F	------	OK ABOVE DIODES OK
3CS6	3.0	ET-1562-7	11	15	B	600	GRID NO. 1 MAKE GAS TEST
3CS6	3.0	ET-7562-1	0	31	B	750	GRID NO. 3 MAKE NO GAS TEST
3CU3	3.0	HS-0X00-0	0	85	F	------	OK ABOVE DIODES OK
3CV3	3.0	HS-0000-0	0	84	F	------	CAP=P OK ABOVE DIODES OK
3CX3	3.0	DY-0X00-0	0	87	F	------	
3CY3	3.0	HS-0X00-0	0	75	F	------	OK ABOVE DIODES OK
3CY5	3.0	ET-1562-0	11	81	B	3000	
3CZ3	3.0	HS-0X00-0	0	85	F	------	OK ABOVE DIODES OK
3DA3	3.0	DY-0X00-0	0	87	F	------	
3DB3	3.0	HS-0X00-0	0	75	F	------	OK ABOVE DIODES OK
3DC3	3.0	HS-0X00-0	0	85	F	------	OK ABOVE DIODES OK
3DF3	3.0	DY-0X00-0	0	87	F	------	
3DG4	3.0	DR-0700-0	0	89	D	------	Plate No. 1
3DG4	3.0	DR-0500-0	0	89	D	------	Plate No. 2
3DH3	3.0	DY-0X00-0	0	88	F	------	OK ABOVE DIODES OK
3DJ3	3.0	HS-0X00-0	0	88	F	------	OK ABOVE DIODES OK
3DK6	3.0	ET-1562-7	12	83	A	3300	
3DR3	3.0	DS-0X00-0	0	88	F	------	OK ABOVE DIODES OK
3DS3	3.0	DS-0X00-0	0	88	F	------	OK ABOVE DIODES OK
3DT6	3.0	ET-1562-7	23	15	A	600	Grid No. 1
3DT6	3.0	ET-7562-1	16	0	B	500	Grid No. 3
3DX4	3.0	ET-2105-0	29	85	A	3800	
3DZ4	3.0	ET-2105-0	35	87	A	4000	
3EA5	3.0	ET-1562-0	11	86	A	4000	
3EH7	3.0	EV-2781-9	15	87	A	3300	
3EJ7	3.0	EV-2781-9	10	87	A	4000	
3ER5	3.0	ET-2567-0	10	89	A	5000	
3EV5	3.0	ET-1562-0	21	87	A	4000	
3FH5	3.0	ET-2507-0	14	87	A	4600	
3FS5	3.0	ET-1567-0	10	85	A	3500	
3GK5	3.0	ET-2507-6	19	89	A	5200	
3GW5	3.0	ET-2105-0	20	88	A	5000	
3HA5	2.5	ET-1507-6	20	87	A	4600	
3HK5	3.0	ET-1502-0	19	88	A	5000	
3HM5	3.0	ET-1507-6	20	87	A	4600	

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.		NOTATIONS
3HQ5	3.0	ET-1507-6	20	87	A	4400	
3JC6	3.0	EV-2781-9	11	88	A	5000	
3JD6	3.0	EV-2781-9	10	83	A	3200	
3JH6	3.0	ET-1562-7	11	84	A	3700	
3KF8	3.0	EV-7821-9	10	17	A	700	Pent. No. 1
3KF8	3.0	EV-7321-6	10	17	A	700	Pent. No. 2
3KT6	3.0	EV-2781-9	15	81	A	2350	
3V4	3.0	HR-6230-0	35	68	A	1650	
4AU6	4.3	ET-1567-2	11	76	A	2300	
4AV6	4.3	ET-1702-5	12	58	A	1250	Triode Sect.
4AV6	4.3	ET-0602-0	0	26	C	------	Diode No. 1
4AV6	4.3	ET-0502-0	0	26	C	------	Diode No. 2
4BC5	4.3	ET-1562-0	11	78	A	2500	
4BC8	4.3	EV-7608-9	16	90	A	6200	Triode No. 1
4BC8	4.3	EV-2103-9	16	90	A	6200	Triode No. 2
4BN6	4.3	ET-2751-6	6	27	B	700	Limiter Grid
4BN6	4.3	ET-6751-2	13	0	B	500	Quadrature Grid
4BQ7A	4.3	EV-7608-9	13	90	A	6400	Triode No. 1
4BQ7A	4.3	EV-2103-9	13	90	A	6400	Triode No. 2
4BS8	4.3	EV-7608-9	19	87	A	4500	Triode No. 1
4BS8	4.3	EV-2103-9	19	87	A	4500	Triode No. 2
4BU8	4.3	EV-7821-9	11	30	F	------	Pent. No. 1
4BU8	4.3	EV-7321-6	11	30	F	------	Pent. No. 2
4BZ6	4.3	ET-1562-7	11	81	A	3000	
4BZ7	4.3	EV-7608-9	16	87	A	4500	Triode No. 1
4BZ7	4.3	EV-2103-9	16	87	A	4500	Triode No. 2
4CB6	4.3	ET-1562-7	11	82	A	3300	
4CS6	4.3	ET-1562-7	11	15	B	600	GRID NO. 1 MAKE GAS TEST
4CS6	4.3	ET-7562-1	0	31	B	750	GRID NO. 3 MAKE NO GAS TEST
4CY5	4.3	ET-1562-0	11	81	B	3000	
4DE6	4.3	ET-1562-7	11	81	A	3000	
4DK6	4.3	ET-1562-7	12	83	A	3300	
4DT6	4.3	ET-1562-7	23	15	A	600	Grid No. 1
4DT6	4.3	ET-7562-1	16	0	B	500	Grid No. 3
4EH7	4.3	EV-2781-9	15	87	A	3300	
4EJ7	4.3	EV-2781-9	10	87	A	4000	
4ES8	4.3	EV-7608-0	22	92	A	7500	Triode No. 1
4ES8	4.3	EV-2103-0	22	92	A	7500	Triode No. 2
4EW6	4.3	ET-1562-7	11	84	A	3700	
4GK5	4.3	ET-2507-6	19	87	A	5200	
4GM6	4.3	ET-1562-7	10	86	A	5000	
4GS8	4.3	EV-7821-9	0	38	F	------	PENT. NO. 1. OK ABOVE 500 ON 3000 SCALE.
4GS8	4.3	EV-7321-6	0	38	F	------	PENT. NO. 2. OK ABOVE 500 ON 3000 SCALE.
4GX7	4.3	EV-2671-0	11	84	A	3200	Pent. Sect.
4GX7	4.3	EV-9801-0	18	89	A	4800	Triode Sect.
4GZ5	4.3	ET-2761-0	20	86	A	4000	
4HA5	4.3	ET-1507-6	20	87	A	4600	
4HA7‡	4.3	B3-9X04-0	20	76	A	2500	Triode No. 1
4HA7	4.3	B3-A203-0	16	16	A	750	Triode No. 2

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.	NOTATIONS
4HC7‡	4.3	B3-9X04-0	12	84	A 3500	Triode No. 1
4HC7	4.3	B3-A203-0	19	27	A 700	Triode No. 2
4HK5	4.3	ET-1502-0	19	90	A 5900	
4HM5	4.3	ET-1507-6	20	87	A 4600	
4HM6	4.3	EV-2781-9	11	87	A 4700	
4HQ5	4.3	ET-1507-6	20	87	A 4400	
4HS8	4.3	EV-7821-9	10	15	A 600	Pent. No. 1
4HS8	4.3	EV-7321-6	10	15	A 600	Pent. No. 2
4HT6	4.3	EV-2781-9	10	87	A 4600	
4JC6	4.3	EV-2781-9	10	89	A 5600	
4JD6	4.3	EV-2783-9	10	83	B 2600	
4JH6	4.3	ET-1562-7	11	84	A 3700	
4JK6	4.3	ET-1562-7	10	86	A 4800	
4JL6	4.3	ET-1562-7	16	85	A 4200	
4JW8	4.3	EV-2367-0	17	87	A 2200	Pent. Sect.
4JW8	4.3	EV-9108-0	19	66	A 1600	Triode Sect.
4KE8	4.3	EV-2637-0	11	85	A 3700	Pent. Sect.
4KE8	4.3	EV-9108-0	20	87	A 4500	Triode Sect.
4KF8	4.3	EV-7821-9	10	17	A 700	Pent. No. 1
4KF8	4.3	EV-7321-6	10	17	A 700	Pent. No. 2
4KT6	4.3	EV-2781-9	15	81	A 2350	
4LJ8	4.3	EV-9678-0	15	75	A 2800	Pent. Sect.
4LJ8	4.3	EV-1203-0	24	75	A 2600	Triode Sect.
4LU6	4.3	ET-1562-7	11	86	A 4200	
4MK8	4.3	EV-7821-9	11	30	F	Pent. No. 1
4MK8	4.3	EV-7321-6	11	30	F	Pent. No. 2
5AM8	5.0	EV-2631-9	11	79	A 2700	Pent. Sect.
5AM8	5.0	EV-0807-0	0	78	C	Diode Sect.
5AN8	5.0	EV-8679-1	11	81	A 3000	Pent. Sect.
5AN8	5.0	EV-2173-6	24	83	A 3300	Triode Sect.
5AQ5	5.0	ET-1562-0	11	86	A 4100	
5AR4	5.0	JS-0600-0	0	90	D	Plate No. 1
5AR4	5.0	JS-0400-0	0	90	D	Plate No. 2
5AS8	5.0	EV-2913-7	11	81	A 3000	Pent. Sect.
5AS8	5.0	EV-0608-0	0	78	C	Diode Sect.
5AT8	5.0	EV-9673-8	12	81	A 3000	Pent. Sect.
5AT8	5.0	EV-1203-8	20	84	A 3500	Triode Sect.
5AU4	7.5	JS-0600-0	0	83	D	Plate No. 1
5AU4	7.5	JS-0400-0	0	75	D	Plate No. 2
5AV8	5.0	EV-6987-0	11	81	A 3000	Pent. Sect.
5AV8	5.0	EV-2301-0	24	83	A 3300	Triode Sect.
5B8	5.0	EV-6987-1	11	81	A 3000	Pent. Sect.
5B8	5.0	EV-2301-9	24	83	A 3300	Triode Sect.
5BC3‡	5.0	BT-0900-0	0	74	D	PLATE NO. 1 USE ADAPTER SA-4, 1050-144
5BC3	5.0	BT-0500-0	0	82	D	PLATE NO. 2 NOTE 3
Model 6000 A:		No Adapter Required.				
5BE8	5.0	EV-9678-3	11	73	A 2000	Pent. Sect.
5BE8	5.0	EV-1203-0	12	90	A 6200	Triode Sect.
5BK7A	5.0	EV-7608-9	20	85	A 4000	Triode No. 1
5BK7A	5.0	EV-2103-9	20	85	A 4000	Triode No. 2

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.	NOTATIONS
5BQ7A	5.0	EV-7608-9	13	90	A 6400	Triode No. 1
5BQ7A	5.0	EV-2103-9	13	90	A 6400	Triode No. 2
5BR8	5.0	EV-9678-0	11	73	A 2000	Pent. Sect.
5BR8	5.0	EV-1203-0	12	90	A 6200	Triode Sect.
5BT8	5.0	EV-8679-0	19	75	A 2200	Pent. Sect.
5BT8	5.0	EV-0103-0	0	63	C	Diode No. 1
5BT8	5.0	EV-0203-0	0	63	C	Diode No. 2
5BW8	5.0	EV-6987-0	11	73	A 2000	Pent. Sect.
5BW8	5.0	EV-0302-0	0	77	C	Diode No. 1
5BW8	5.0	EV-0102-0	0	77	C	Diode No. 2
5CG8	5.0	EV-9678-0	12	81	A 3000	Pent. Sect.
5CG8	5.0	EV-1203-0	20	84	A 3500	Triode Sect.
5CL8	5.0	EV-9678-0	10	84	A 3500	Tetrode Sect.
5CL8	5.0	EV-1203-0	12	89	A 6000	Triode Sect.
5CM8	5.0	EV-2673-0	11	81	A 3000	Pent. Sect.
5CM8	5.0	EV-9108-0	12	65	A 1500	Triode Sect.
5CQ8	5.0	EV-2637-0	10	79	A 2600	Tetrode Sect.
5CQ8	5.0	EV-9108-0	11	87	A 4300	Triode Sect.
5CZ5	5.0	EV-3917-0	10	87	A 4500	
5DH8	5.0	EV-9678-0	10	83	A 3400	Pent. Sect.
5DH8	5.0	EV-1203-0	15	78	A 2500	Triode Sect.
5DJ4	5.0	JS-0600-0	0	70	D	Plate No. 1
5DJ4	5.0	JS-0400-0	0	65	D	Plate No. 2
5EA8	5.0	EV-2637-0	11	79	A 2600	Pent. Sect.
5EA8	5.0	EV-9108-0	11	89	A 5000	Triode Sect.
5ES8	5.0	EV-7608-0	22	92	A 7500	Triode No. 1
5ES8	5.0	EV-2103-0	22	92	A 7500	Triode No. 2
5EU8	5.0	EV-7198-0	11	79	A 2600	Pent. Sect.
5EU8	5.0	EV-2306-0	11	89	A 5000	Triode Sect.
5EW6	5.0	ET-1562-7	11	84	A 3700	
5FG7	5.0	EV-9678-0	10	82	A 3000	Pent. Sect.
5FG7	5.0	EV-1203-0	18	88	A 4750	Triode Sect.
5FV8	5.0	EV-9678-0	10	80	A 2750	Pent. Sect.
5FV8	5.0	EV-1203-0	15	89	A 5500	Triode Sect.
5GH8	5.0	EV-2637-0	11	82	A 3000	Pent. Sect.
5GH8	5.0	EV-9108-0	21	85	A 3900	Triode Sect.
5GM6	5.0	ET-1562-7	10	86	A 5000	
5GS7	5.0	EV-9678-0	10	85	A 3500	Pent. Sect.
5GS7	5.0	EV-1203-0	31	85	A 3750	Triode Sect.
5GX6	5.0	ET-1562-7	12	67	A 1600	
5GX7	5.0	EV-2671-0	11	84	A 3200	Pent. Sect.
5GX7	5.0	EV-9801-0	18	89	A 4800	Triode Sect.
5HA7‡	5.0	B3-9X04-0	20	76	A 2500	Triode No. 1
5HA7	5.0	B3-A203-0	16	16	A 750	Triode No. 2
5HB7	5.0	EV-2671-0	10	79	A 3100	Pent. Sect.
5HB7	5.0	EV-9801-0	11	89	A 4500	Triode Sect.
5HC7‡	5.0	B3-9X04-0	12	84	A 3500	Triode No. 1
5HC7	5.0	B3-A203-0	19	27	A 700	Triode No. 2
5HG8	5.0	EV-2893-0	10	84	A 3600	Pent. Sect.
5HG8	5.0	EV-6703-0	32	82	A 3200	Triode Sect.
5HZ6	5.0	ET-1562-7	10	65	A 1400	

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.	NOTATIONS
5J6	5.0	ET-5207-0	21	81	A 3000	Triode No. 1
5J6	5.0	ET-6107-0	21	81	A 3000	Triode No. 2
5JK6	5.0	ET-1562-7	10	86	A 4800	
5JL6	5.0	ET-1562-7	16	85	A 4200	
5JW8	5.0	EV-2637-0	17	87	A 2200	Pent. Sect.
5JW8	5.0	EV-9108-0	19	66	A 1600	Triode Sect.
5KD8	5.0	EV-2637-0	10	79	A 2600	Pent. Sect.
5KD8	5.0	EV-9108-0	19	89	A 5200	Triode Sect.
5KE8	5.0	EV-2637-0	11	85	A 3700	Pentode Sect.
5KE8	5.0	EV-9108-0	20	87	A 4500	Triode Sect.
5KZ8	5.0	EV-2673-0	12	82	A 3200	Pent. Sect.
5KZ8	5.0	EV-9108-0	22	84	A 3600	Triode Sect.
5LJ8	5.0	EV-9678-0	15	75	A 2800	Pent. Sect.
5LJ8	5.0	EV-1203-0	24	75	A 2600	Triode Sect.
5MB8	5.0	EV-9678-0	8	84	A 4000	Pent. Sect.
5MB8	5.0	EV-1203-0	13	88	A 4800	Triode Sect.
5MQ8	5.0	EV-2637-0	15	80	A 3000	Pent. Sect.
5MQ8	5.0	EV-9108-0	20	83	A 3300	Triode Sect.
5R4	5.0	JS-0600-0	0	45	D	Plate No. 1
5R4	5.0	JS-0400-0	0	35	D	Plate No. 2
5T8	5.0	EV-8907-0	11	56	A 1200	Triode Sect.
5T8	5.0	EV-0607-0	0	77	C	Diode No. 1
5T8	5.0	EV-0203-0	0	77	C	Diode No. 2
5T8	5.0	EV-0107-0	0	77	C	Diode No. 3
5U4G	5.0	JS-0600-0	0	45	D	Plate No. 1
5U4G	5.0	JS-0400-0	0	35	D	Plate No. 2
5U4GA,B	5.0	JS-0600-0	0	70	D	Plate No. 1
5U4GA,B	5.0	JS-0400-0	0	65	D	Plate No. 2
5U8	5.0	EV-2637-0	11	73	A 2000	Pent. Sect.
5U8	5.0	EV-9108-0	12	90	A 6200	Triode Sect.
5U9‡	6.3	FW-3782-4	10	83	A 3300	PENT. SECT. USE ADAPTER SA-11, 1050-177 MODEL 6000, 6005 NOTE 3
5U9	6.3	FW-X901-0	29	81	A 3000	Triode Sect.
5V3	6.3	JS-0600-4	0	80	D	Plate No. 1
5V3	6.3	JS-0400-6	0	70	D	Plate No. 2
5V4	5.0	JS-0600-0	0	85	D	Plate No. 1
5V4	5.0	JS-0400-0	0	85	D	Plate No. 2
5V6	5.0	HS-5348-0	13	86	A 4100	
5V9‡	5.0	FW-3741-2	10	48	B 1000	HEPT. SECT. USE ADAPTER SA-11, 1050-177 MODEL 6000, 6005 NOTE 3
5V9	5.0	FW-8X09-0	22	81	A 3000	Triode Sect.
5X8	5.0	EV-7986-1	12	81	A 3000	Pent. Sect.
5X8	5.0	EV-2306-1	20	84	A 3500	Triode Sect.
5X9‡	6.3	FW-3782-4	10	84	A 3600	PENT. SECT. USE ADAPTER SA-11, 1050-177 MODEL 6000, 6005 NOTE 3
5X9	6.3	FW-X901-0	12	81	A 3000	Triode Sect.
5Y3	5.0	JS-0600-0	0	22	D	Plate No. 1
5Y3	5.0	JS-0400-0	0	18	D	Plate No. 2
6AB4	6.3	ET-6107-0	10	85	A 4000	

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.	NOTATIONS
6AB9‡	6.3	FW-978X-0	15	81	A 3000	TETRODE NO. 1. USE ADAPTER SA-11, 1050-177 MODEL 6000, 6005 NOTE 3
6AB9	6.3	FW-3124-0	15	81	A 3000	Tetrode No. 2
6AC7	6.3	HS-4865-3	11	81	A 3000	
6AC9‡	6.3	B3-9AX8-7	10	87	A 4200	Pent. Sect.
6AC9	6.3	B3-0304-0	0	85	C	Diode No. 1
6AC9	6.3	B3-0203-0	0	85	C	Diode No. 2
6AC10‡	6.3	B3-9X04-0	14	85	A 3700	Triode No. 1
6AC10	6.3	B3-7506-0	14	85	A 3700	Triode No. 2
6AC10	6.3	B3-A203-0	14	85	A 3700	Triode No. 3
6AD10‡	6.3	B3-3762-5	17	62	A 1900	Pent. No. 1
6AD10	6.3	B3-8AX9-0	7	89	A 3800	Pent. No. 2
6AF3	6.3	EV-020X-0	0	86	D	
6AF4	6.3	ET-2105-0	36	85	A 4000	
6AF9‡	6.3	FW-8X97-0	13	88	A 5000	PENT. NO. 1. USE ADAPTER SA-11, 1050-177 MODEL 6000, 6005 NOTE 3
6AF9	6.3	FW-1432-0	13	83	A 3300	Pent. No. 2
6AF11‡	6.3	B3-A2X9-0	10	88	A 4900	Pent. Sect.
6AF11	6.3	B3-6805-0	18	77	A 2400	Triode No. 1
6AF11	6.3	B3-3407-0	10	80	A 2800	Triode No. 2
6AG5	6.3	ET-1562-0	11	78	A 2500	
6AG7	6.3	HS-4865-1	11	88	A 5000	
6AG9‡	6.3	B3-A2X9-4	19	78	A 2500	Pent. Sect.
6AG9	6.3	B3-5706-0	14	87	A 4600	Triode Sect.
6AG11‡	6.3	B3-8709-0	16	86	A 4000	Triode No. 1
6AG11	6.3	B3-5604-0	16	86	A 4000	Triode No. 2
6AG11	6.3	B3-0X0A-0	0	80	C	Diode No. 1
6AG11	6.3	B3-0302-0	0	80	C	Diode No. 2
6AH9‡	6.3	B3-5A87-9	10	87	A 5200	Pentode Sect.
6AH9	6.3	B3-2304-0	27	77	A 2350	Triode Sect.
6AK5	6.3	ET-1562-0	24	65	A 1500	
6AK6	6.3	ET-1567-2	20	74	A 2100	
6AK9‡	6.3	B3-8597-0	30	85	A 4150	Pent. Sect.
6AK9	6.3	B3-XA07-0	18	75	A 2400	Triode No. 1
6AK9	6.3	B3-3207-0	26	59	A 1750	Triode No. 2
6AK10‡	6.3	B3-9X04-0	14	85	A 4500	Triode No. 1
6AK10	6.3	B3-7506-0	14	85	A 4500	Triode No. 2
6AK10	6.3	B3-A203-0	14	85	A 4500	Triode No. 3
6AL3	6.3	EV-090X-0	0	93	D	
6AL5	6.3	ET-0701-6	0	78	C	Diode No. 1
6AL5	6.3	ET-0205-6	0	78	C	Diode No. 2
6AL9‡	6.3	B3-A2X9-4	5	91	A 9000	Pent. Sect.
6AL9	6.3	B3-5706-0	9	88	A 6300	Triode Sect.
6AL11‡	6.3	B3-8AX9-0	14	87	A 4300	Pent. No. 1
6AL11	6.3	B3-3672-4	20	21	A 620	Pent. No. 2
6AM8	6.3	EV-2631-9	11	79	A 2700	Pent. Sect.
6AM8	6.3	EV-0807-0	0	78	C	Diode Sect.
6AN4	6.3	ET-2105-0	13	89	A 5500	
6AN5	6.3	ET-1567-0	13	85	B 4000	
6AN8	6.3	EV-8679-1	11	81	A 3000	Pent. Sect.
6AN8	6.3	EV-2173-6	24	83	A 3300	Triode Sect.

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.		NOTATIONS
6AQ5	6.3	ET-1562-0	11	86	A	4100	
6AR11‡	6.3	B3-X89A-7	10	81	A	2700	Pent. No. 1
6AR11	6.3	B3-5236-4	10	81	A	2700	Pent. No. 2
6AS6	6.3	ET-1562-7	11	48	B	1000	
6AS7	7.5	HY-4506-2	100	79	A	2600	Triode No. 1
6AS7	7.5	HY-1203-5	100	79	A	2600	Triode No. 2
6AS8	6.3	EV-2913-7	11	81	A	3000	Pent. Sect.
6AS8	6.3	EV-0608-0	0	78	C	.....	Diode Sect.
6AS11‡	6.3	B3-A2X9-0	10	88	A	5000	Pent. Sect.
6AS11	6.3	B3-6805-0	14	85	A	3800	Triode No. 1
6AS11	6.3	B3-3407-0	16	83	A	3300	Triode No. 2
6AT6	6.3	ET-1702-0	10	60	A	1300	Triode Sect.
6AT6	6.3	ET-0602-0	0	26	C	.....	Diode No. 1
6AT6	6.3	ET-0502-0	0	26	C	.....	Diode No. 2
6AT8	6.3	EV-9673-8	12	81	A	3000	Pent. Sect.
6AT8	6.3	EV-1203-8	20	84	A	3500	Triode Sect.
6AU4	6.3	HY-0503-0	0	89	D	.....	
6AU5	6.3	HS-1583-0	25	88	A	5200	
6AU6	6.3	ET-1567-2	11	76	A	2300	
6AU8	6.3	EV-7986-0	11	86	A	4200	Pent. Sect.
6AU8	6.3	EV-2301-0	15	86	A	4000	Triode Sect.
6AV6	6.3	ET-1702-5	12	58	A	1250	Triode Sect.
6AV6	6.3	ET-0602-0	0	26	C	.....	Diode No. 1
6AV6	6.3	ET-0502-0	0	26	C	.....	Diode No. 2
6AV11‡	6.3	B3-9X04-0	22	78	A	2500	Triode No. 1
6AV11	6.3	B3-7506-0	22	78	A	2500	Triode No. 2
6AV11	6.3	B3-A203-0	22	78	A	2500	Triode No. 3
6AW8	6.3	EV-7986-0	10	88	A	5000	Pent. Sect.
6AW8	6.3	EV-2301-0	15	78	A	2500	Triode Sect.
6AX3‡	6.3	B3-0407-0	0	82	D	.....	
6AX4	6.3	HY-0503-0	0	82	D	.....	
6AX5	6.3	HS-0508-3	0	20	D	.....	Plate No. 1
6AX5	6.3	HS-0308-5	0	20	D	.....	Plate No. 2
6AY3‡	6.3	EV-0209-0	0	87	D	.....	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000 A: No Adapter Required.							
6AY11‡	6.3	B3-8709-0	20	22	A	660	Triode No. 1
6AY11	6.3	B3-5604-0	20	22	A	660	Triode No. 2
6AY11	6.3	B3-0X0A-0	0	77	C	.....	Diode No. 1
6AY11	6.3	B3-0302-0	0	77	C	.....	Diode No. 2
6AZ8	6.3	EV-6123-0	11	81	A	3000	Pent. Sect.
6AZ8	6.3	EV-9807-0	24	83	A	3300	Triode Sect.
6B10‡	6.3	B3-5607-0	24	78	A	2500	Triode No. 1
6B10	6.3	B3-3402-0	24	78	A	2500	Triode No. 2
6B10	6.3	B3-0X09-0	0	78	C	.....	Diode No. 1
6B10	6.3	B3-0809-0	0	78	C	.....	Diode No. 2
6BA3‡	6.3	EV-0209-0	0	84	D	.....	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000 A: No Adapter Required.							
6BA5	6.3	DW-1578-0	19	75	A	2150	
6BA6	6.3	ET-1567-2	11	72	A	1900	
6BA7	6.3	EV-7913-2	0	31	B	750	Ampl. Sect.
6BA7	6.3	EV-2103-7	16	88	A	5000	Osc. Sect.

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.		NOTATIONS
6BA8	6.3	EV-7986-0	11	88	A	5000	Pent. Sect.
6BA8	6.3	EV-2301-0	30	79	A	2700	Triode Sect.
6BA11‡	6.3	B3-4638-7	10	15	A	600	Pent. No. 1
6BA11	6.3	B3-4238-5	10	15	A	600	Pent. No. 2
6BA11	6.3	B3-9A0X-0	30	62	A	1600	Triode Sect.
6BC4	6.3	EV-2106-0	12	91	A	7000	
6BC5	6.3	ET-1562-0	11	78	A	2500	
6BC7	6.3	EV-0809-3	0	80	C	.....	Diode No. 1
6BC7	6.3	EV-0607-3	0	80	C	.....	Diode No. 2
6BC7	6.3	EV-0201-3	0	80	C	.....	Diode No. 3
6BC8	6.3	EV-7608-9	16	90	A	6200	Triode No. 1
6BC8	6.3	EV-2103-9	16	90	A	6200	Triode No. 2
6BD11‡	6.3	B3-A2X9-0	13	87	A	4500	Pent. Sect.
6BD11	6.3	B3-6805-0	17	78	A	2500	Triode No. 1
6BD11	6.3	B3-3407-0	11	80	A	2750	Triode No. 2
6BE3‡	6.3	B3-0X07-0	0	89	D	.....	
6BE6	6.3	ET-7562-1	0	35	B	800	AMPL. SECT. MAKE NO GAS TEST
6BE6	6.3	ET-1602-7	20	90	A	6500	OSC. SECT. MAKE GAS TEST
6BF11‡	6.3	B3-8AX9-0	25	88	A	5000	Pent. No. 1
6BF11	6.3	B3-3762-5	13	7	A	550	Pent. No. 2
6BH3‡	6.3	EV-0209-0	0	87	D	.....	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000 A: No Adapter Required.							
6BH6	6.3	ET-1562-7	12	73	A	2000	
6BH8	6.3	EV-7986-0	7	88	A	5000	Pent. Sect.
6BH8	6.3	EV-2301-0	27	83	A	3300	Triode Sect.
6BH11‡	6.3	B3-8X9A-0	10	84	A	3500	Pent. Sect.
6BH11	6.3	B3-6705-0	18	89	A	5100	Triode No. 1
6BH11	6.3	B3-4302-0	18	89	A	5100	Triode No. 2
6BJ3‡	6.3	B3-0X07-0	0	88	D	.....	
6BJ7	6.3	EV-0809-3	0	80	C	.....	Diode No. 1
6BJ7	6.3	EV-0607-3	0	80	C	.....	Diode No. 2
6BJ7	6.3	EV-0201-3	0	80	C	.....	Diode No. 3
6BJ8	6.3	EV-8709-0	27	80	A	2800	Triode Sect.
6BJ8	6.3	EV-0603-0	0	78	C	.....	Diode No. 1
6BJ8	6.3	EV-0102-0	0	78	C	.....	Diode No. 2
6BK4	6.3	HS-0501-X	0	45	C	.....	
6BK7	6.3	EV-7608-9	20	85	A	4000	Triode No. 1
6BK7	6.3	EV-2103-9	20	85	A	4000	Triode No. 2
6BK11‡	6.3	B3-9X04-0	20	39	A	850	Triode No. 1
6BK11	6.3	B3-7506-0	19	7	A	550	Triode No. 2
6BK11	6.3	B3-A203-0	19	7	A	550	Triode No. 3
6BL7	6.3	HY-4506-0	24	88	A	5000	Triode No. 1
6BL7	6.3	HY-1203-0	24	88	A	5000	Triode No. 2
6BL8	6.3	EV-2637-1	12	81	A	3000	Pent. Sect.
6BL8	6.3	EV-9108-6	26	85	A	4000	Triode Sect.
6BM8	6.3	EV-3672-0	24	86	A	4300	Pent. Sect.
6BM8	6.3	EV-1908-0	11	71	A	1900	Triode Sect.
6BN4	6.3	ET-2501-0	19	88	A	5000	
6BN4A	6.3	ET-2501-0	19	86	A	3200	
6BN6	6.3	ET-2751-6	6	27	B	700	Limiter Grid
6BN6	6.3	ET-6751-2	13	0	B	500	Quadrature Grid

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.		NOTATIONS
6BN8	6.3	EV-8709-0	22	48	A	1000	Triode Sect.
6BN8	6.3	EV-0603-0	0	78	C	------	Diode No. 1
6BN8	6.3	EV-0102-0	0	78	C	------	Diode No. 2
6BN11‡	6.3	B3-7A98-X	10	85	A	3800	Pent. No. 1
6BN11	6.3	B3-3542-6	10	85	A	3800	Pent. No. 2
6BQ5	6.3	EV-2793-0	12	90	A	7500	
6BQ6	6.3	HS-5X48-0	42	89	A	5500	
6BQ7A	6.3	EV-7608-9	13	90	A	6400	Triode No. 1
6BQ7A	6.3	EV-2103-9	13	90	A	6400	Triode No. 2
6BR8	6.3	EV-9678-0	11	73	A	2000	Pent. Sect.
6BR8	6.3	EV-1203-0	12	90	A	6200	Triode Sect.
6BS3‡	6.3	EV-0209-0	0	83	D	------	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000 A:		No Adapter Required.					
6BU8	6.3	EV-7821-9	11	30	F	------	Pent. No. 1
6BU8	6.3	EV-7321-6	11	30	F	------	Pent. No. 2
6BV11‡	6.3	B3-7X98-A	10	73	A	2000	Pent. No. 1
6BV11	6.3	B3-6345-2	10	73	A	2000	Pent. No. 2
6BW3‡	6.3	B3-0407-0	0	89	D	------	OK ABOVE DIODES OK
6BW8	6.3	EV-6987-0	11	73	A	2000	Pent. Sect.
6BW8	6.3	EV-0302-0	0	77	C	------	Diode No. 1
6BW8	6.3	EV-0102-0	0	77	C	------	Diode No. 2
6BW11‡	6.3	B3-A89X-7	7	85	A	4250	Pentode No. 1
6BW11	6.3	B3-3542-6	10	82	A	3300	Pentode No. 2
6BY6	6.3	ET-1562-7	12	56	A	1200	Grid No. 1
6BY6	6.3	ET-7562-1	16	0	B	500	Grid No. 3
6BY8	6.3	EV-1789-2	11	76	A	2300	Pent. Sect.
6BY8	6.3	EV-0603-0	0	78	C	------	Diode Sect.
6BY11‡	6.3	B3-8AX9-0	45	83	A	3800	Pent. No. 1
6BY11	6.3	B3-3762-5	15	40	A	1000	Pent. No. 2
6BZ3‡	6.3	B3-0X07-0	0	86	C	------	
6BZ6	6.3	ET-1562-7	11	81	A	3000	
6BZ7	6.3	EV-7608-9	16	87	A	4500	Triode No. 1
6BZ7	6.3	EV-2103-9	16	87	A	4500	Triode No. 2
6C4	6.3	ET-6107-0	25	75	A	2200	
6C9‡	6.3	EV-7986-0	15	85	A	3200	Tetrode No. 1
6C9	6.3	EV-132X-0	15	85	A	3200	Tetrode No. 2
6C10‡	6.3	B3-9X04-0	12	58	A	1250	Triode No. 1
6C10	6.3	B3-7506-0	12	58	A	1250	Triode No. 2
6C10	6.3	B3-A203-0	12	58	A	1250	Triode No. 3
6CA4	6.3	EV-0703-0	0	62	D	------	Plate No. 1
6CA4	6.3	EV-0103-0	0	62	D	------	Plate No. 2
6CA5	6.3	DU-2761-0	20	89	A	5500	
6CA7	6.3	HS-5348-1	23	90	A	6000	
6CA11‡	6.3	B3-8AX9-7	20	86	A	4250	Pent. Sect.
6CA11	6.3	B3-6405-0	20	73	A	2350	Triode No.1
6CA11	6.3	B3-3207-0	20	75	A	2500	Triode No.2
6CB5	7.5	HS-4X13-0	40	92	A	7000	
6CB6	6.3	ET-1562-7	11	82	A	3300	
6CD3‡	6.3	B3-0X07-0	0	93	D	------	
6CD6	6.3	HS-5X83-0	35	90	A	6500	
6CE3‡	6.3	B3-0407-0	0	86	C	------	
6CE5	6.3	ET-1562-0	11	81	A	3000	

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.		NOTATIONS
6CG3‡	6.3	B3-0407-0	0	91	D	------	
6CG7	6.3	EV-7608-9	23	79	A	2600	Triode No. 1
6CG7	6.3	EV-2103-9	23	79	A	2600	Triode No. 2
6CG8	6.3	EV-9678-0	12	81	A	3000	Pent. Sect.
6CG8	6.3	EV-1203-0	20	84	A	3500	Triode Sect.
6CH3‡	6.3	EV-0209-0	0	91	D	------	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000 A:		No Adapter Required.					
6CJ3‡	6.3	EV-0209-0	0	86	C	------	USE ADAPTER SA-4 1050-144. NOTE 3
Model 6000 A:		No Adapter Required.					
6CK3‡	6.3	EV-0209-0	0	86	C	------	USE ADAPTER SA-4, 1050:144. NOTE 3
Model 6000 A:		No Adapter Required.					
6CL3‡	6.3	EV-0209-0	0	86	C	------	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000 A:		No Adapter Required.					
6CL5	6.3	HS-4X13-0	55	89	A	6500	
6CL6	6.3	EV-2631-7	11	88	A	5000	
6CL8	6.3	EV-9678-0	10	84	A	3500	Tetrode Sect.
6CL8	6.3	EV-1203-0	12	89	A	6000	Triode Sect.
6CM3‡	6.3	EV-0279-0	0	90	D	------	PLATE TO SCREEN SHORT NORMAL
Model 6000 A:		No Adapter Required.					USE ADAPTER SA-4, 1050-144. NOTE 3
6CM6	6.3	EV-3917-0	11	86	A	4100	
6CM7	6.3	EV-7603-0	27	73	A	2000	Triode No. 1
6CM7	6.3	EV-8109-0	24	87	A	4400	Triode No. 2
6CN7	6.3	EV-7806-0	11	56	A	1200	Triode Sect.
6CN7	6.3	EV-0203-0	0	77	C	------	Diode No. 1
6CN7	6.3	EV-0103-0	0	77	C	------	Diode No. 2
6CQ4	6.3	HY-0503-0	0	89	D	------	
6CQ8	6.3	EV-2637-0	10	79	A	2600	Tetrode Sect.
6CQ8	6.3	EV-9108-0	11	87	A	4300	Triode Sect.
6CS6	6.3	ET-1562-7	11	15	B	600	GRID NO. 1 MAKE GAS TEST
6CS6	6.3	ET-7562-1	0	31	B	750	GRID NO. 3 MAKE NO GAS TEST
6CS7	6.3	EV-7608-0	22	75	A	2200	Triode No. 1
6CS7	6.3	EV-3109-0	27	87	A	4500	Triode No. 2
6CT3	6.3	EV-0209-0	0	94	D	------	OK ABOVE DIODES OK
6CU5	6.3	ET-2761-0	11	91	B	7000	
6CU8	6.3	EV-7236-1	11	81	A	3000	Pent. Sect.
6CU8	6.3	EV-8901-0	24	83	A	3300	Triode Sect.
6CW4‡	6.3	DR-4208-0	23	79	A	2600	USE ADAPTER SA-3, 1050-127. NOTE 3
Model 6000 A:							
6CW4	6.3	13-4208-0	23	79	A	2600	
6CW5	6.3	EV-2793-0	40	89	A	5500	
6CX8	6.3	EV-7986-0	16	83	A	3300	Pent. Sect.
6CX8	6.3	EV-2301-0	15	81	A	2900	Triode Sect.
6CY5	6.3	ET-1562-0	11	81	B	3000	
6CY7	6.3	EV-7608-0	10	53	A	1100	Triode No. 1
6CY7	6.3	EV-2109-0	60	86	A	4000	Triode No. 2
6CZ5	6.3	EV-3917-0	10	87	A	4500	
6D10‡	6.3	B3-9X04-0	18	78	A	2500	Triode No. 1
6D10	6.3	B3-7506-0	18	78	A	2500	Triode No. 2
6D10	6.3	B3-A203-0	18	78	A	2500	Triode No. 3

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.		NOTATIONS
6DA4	6.3	HY-0503-0	0	86	D	.....	
6DA5	6.3	EV-19X2-0	Vary	100	F	.....	Connect a 1
megohm resistor from cap lead to Loctal Test Socket Pin No. 7.							
Vary Bias to vary beam angle.							
6DB5	6.3	EV-3912-0	11	91	B	7500	
6DC6	6.3	ET-1562-7	10	84	A	3500	
6DE4	6.3	HY-0503-0	0	89	D	.....	
6DE6	6.3	ET-1562-7	11	81	A	3000	
6DE7	6.3	EV-7608-0	27	73	A	2000	Triode No. 1
6DE7	6.3	EV-2109-0	54	89	A	6500	Triode No. 2
6DG6	6.3	HS-5348-0	11	91	B	7500	
6DJ8	6.3	EV-7608-0	22	91	A	7000	Triode No. 1
6DJ8	6.3	EV-2103-0	22	91	A	7000	Triode No. 2
6DK3	6.3	EV-020X-0	0	86	C	.....	
6DK6	6.3	ET-1562-7	12	83	A	3300	
6DL3‡	6.3	EV-070X-0	0	86	C	.....	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000 A:		No Adapter Required.					
6DM4	6.3	HY-0503-0	0	89	D	.....	
6DN3‡	6.3	EV-0709-0	0	86	C	.....	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000 A:		No Adapter Required.					
6DN7	6.3	HY-4506-0	24	73	A	2000	Triode No. 1
6DN7	6.3	HY-1203-0	20	91	A	7500	Triode No. 2
6DQ3‡	6.3	B3-0407-0	0	86	C	.....	
6DQ4	6.3	JX-0503-0	0	86	D	.....	
6DQ5	6.3	HS-1X43-0	43	92	A	7800	
6DQ6	6.3	HS-5X48-0	25	90	B	6000	
6DR4	6.3	ET-6507-0	12	58	A	1250	
6DR7	6.3	EV-7608-0	17	36	A	800	Triode No. 1
6DR7	6.3	EV-2109-0	56	88	A	3600	Triode No. 2
6DS4‡	6.3	DR-4208-0	22	79	A	2600	USE ADAPTER SA-3, 1050-127. NOTE 3
Model 6000 A:							
6DS4	6.3	13-4208-0	22	79	A	2600	
6DS5	6.3	ET-1562-0	13	87	A	4800	
6DT3‡	6.3	B3-0407-0	0	86	C	.....	
6DT4	6.3	HY-0503-0	0	92	D	.....	
6DT5	6.3	EV-3917-0	21	87	A	4400	
6DT6	6.3	ET-1562-7	23	15	A	600	Grid No. 1
6DT6	6.3	ET-7562-1	16	0	B	500	Grid No. 3
6DT8	6.3	EV-7608-9	11	81	A	3000	Triode No. 1
6DT8	6.3	EV-2103-9	11	81	A	3000	Triode No. 2
6DV4‡	6.3	13-6107-0	27	88	A	4600	
6DW4‡	6.3	EV-0209-0	0	89	D	.....	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000 A:		No Adapter Required.					
6DX8	6.3	EV-8697-0	10	90	A	6000	Pent. Sect.
6DX8	6.3	EV-1203-0	18	73	A	2100	Triode Sect.
6DZ4	6.3	ET-2105-0	35	87	A	4000	
6DZ8	6.3	EV-3672-0	23	88	A	5500	Pent. Sect.
6DZ8	6.3	EV-1908-0	19	39	A	850	Triode Sect.
6EA4‡	6.3	B3-0605-X	0	45	C	.....	
6EA5	6.3	ET-1562-0	11	86	A	4000	

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.		NOTATIONS
6EA7	6.3	JX-4506-0	11	65	A	1500	Triode No. 1
6EA7	6.3	JX-1203-0	51	90	A	6500	Triode No. 2
6EA8	6.3	EV-2637-0	11	79	A	2600	Pent. Sect.
6EA8	6.3	EV-9108-0	11	89	A	5000	Triode Sect.
6EB5	6.3	ET-0205-6	0	71	C	.....	Diode No. 1
6EB5	6.3	ET-0701-6	0	71	C	.....	Diode No. 2
6EB8	6.3	EV-7986-0	11	87	A	5100	Pent. Sect.
6EB8	6.3	EV-2301-0	11	70	A	2000	Triode Sect.
6EF4‡	6.3	B3-06X5-9	0	45	C	.....	
6EH4‡	6.3	B3-0605-X	0	45	C	.....	
6EH5	6.3	ET-2761-0	13	88	A	10000	
6EH7	6.3	EV-2781-9	15	87	A	3300	
6EH8	6.3	EV-7986-0	15	75	A	2300	Pent. Sect.
6EH8	6.3	EV-2301-0	20	87	A	4600	Triode Sect.
6EJ4‡	6.3	B3-9605-X	0	45	C	.....	
6EJ7	6.3	EV-2781-9	10	87	A	4000	
6EL4	6.3	HS-0501-X	0	45	C	.....	
6EM5	6.3	EV-3917-0	12	89	A	4300	
6EM7	6.3	HY-4506-0	10	66	A	1500	Triode No. 1
6EM7	6.3	HY-1203-0	53	91	A	5250	Triode No. 2
6EN4	6.3	HS-0501-X	0	45	C	.....	
6EQ7	6.3	EV-2763-1	17	60	A	2400	Pent. Sect.
6EQ7	6.3	EV-0803-0	0	26	C	.....	Diode Sect.
6ER5	6.3	ET-2567-0	10	89	A	5000	
6ES5	6.3	ET-2501-0	10	87	A	4600	
6ES8	6.3	EV-7608-0	22	92	A	7500	Triode No. 1
6ES8	6.3	EV-2103-0	22	92	A	7500	Triode No. 2
6ET7	6.3	EV-7986-0	10	89	A	4750	Pent. Sect.
6ET7	6.3	EV-0301-0	0	21	C	.....	Diode No. 1
6ET7	6.3	EV-0201-0	0	21	C	.....	Diode No. 2
6EU7	6.3	BS-8709-0	12	58	A	1250	Triode No. 1
6EU7	6.3	BS-5604-0	12	58	A	1250	Triode No. 2
6EU8	6.3	EV-7198-0	11	79	A	2600	Pent. Sect.
6EU8	6.3	EV-2306-0	11	89	A	5000	Triode Sect.
6EV5	6.3	ET-1562-0	19	86	A	4000	
6EV7	6.3	EV-7608-0	10	84	A	3600	Triode No. 1
6EV7	6.3	EV-2103-0	10	84	A	3600	Triode No. 2
6EW6	6.3	ET-1562-7	11	84	A	3700	
6EW7	6.3	EV-7608-0	27	72	A	2000	Triode No. 1
6EW7	6.3	EV-2109-0	54	88	A	6000	Triode No. 2
6EX6	6.3	HS-5X83-0	48	91	A	7500	
Tubes indicating shorts: Re-test using HS-5X13-0							
6EY6	6.3	HS-5348-0	28	87	A	4400	
6EZ5	6.3	HS-5348-0	51	71	A	1800	
6EZ8	6.3	EV-9800-0	28	78	A	2500	Triode No. 1
6EZ8	6.3	EV-7600-0	28	78	A	2500	Triode No. 2
6EZ8	6.3	EV-2301-0	18	78	A	2500	Triode No. 3
If no reading is obtained, use selector setting FU- in place of EV-.							
6FA7	6.3	EV-7986-1	10	58	A	1250	Tetrode No. 1
6FA7	6.3	EV-7186-9	10	58	A	1250	Tetrode No. 2
6FA7	6.3	EV-9306-1	0	26	C	.....	Diode Sect.
6FD6	6.3	ET-1657-2	18	45	C	.....	OK ABOVE DIODES OK

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.		NOTATIONS
6FD7	6.3	EV-7608-0	10	68	A	1600	Triode No. 1
6FD7	6.3	EV-2109-0	58	89	A	4500	Triode No. 2
6FE5	6.3	HS-5348-0	30	92	A	8300	
6FG5	6.3	ET-1567-0	10	82	A	2500	
6FG7	6.3	EV-9678-0	10	82	A	3000	Pent. Sect.
6FG7	6.3	EV-1203-0	18	88	A	4750	Triode Sect.
6FH5	6.3	ET-2507-0	14	87	A	4600	
6FH8	6.3	EV-6970-0	25	78	A	2500	TETRODE PLATE NO. 1
6FH8	6.3	EV-6870-0	22	60	A	1300	TETRODE PLATE NO. 2
6FH8	6.3	EV-6170-0	22	60	A	1300	TETRODE PLATE NO. 3
6FH8	6.3	EV-2300-0	23	90	A	5400	Triode Sect.
If no reading is obtained, use selector setting FU- in place of Ev-.							
6FJ7‡	6.3	B3-XA09-0	20	78	A	2300	Triode No. 1
6FJ7	6.3	B3-3507-0	16	91	A	7000	Triode No. 2
6FM7‡	6.3	B3-XA09-0	20	46	A	950	Triode No. 1
6FM7	6.3	B3-8507-0	62	88	A	5250	Triode No. 2
6FM8	6.3	EV-8907-0	11	56	A	1200	Triode Sect.
6FM8	6.3	EV-0601-0	0	77	C	.....	Diode No. 1
6FM8	6.3	EV-0203-0	0	77	C	.....	Diode No. 2
6FQ5	6.3	ET-2507-0	19	87	A	4500	
6FQ5A	6.3	ET-2507-6	19	89	A	5200	
6FQ7	6.3	EV-7608-0	23	79	A	2600	Triode No. 1
6FQ7	6.3	EV-2103-0	23	79	A	2600	Triode No. 2
6FS5	6.3	ET-1567-0	10	85	A	3500	
6FV6	6.3	ET-1567-2	12	85	A	3800	
6FV8	6.3	EV-9678-0	10	80	A	2750	Pent. Sect.
6FV8	6.3	EV-1203-0	15	89	A	5500	Triode Sect.
6FW5	6.3	HS-1583-0	48	90	A	6200	
6FY7‡	6.3	B3-XA09-0	20	32	A	800	Triode No. 1
6FY7	6.3	B3-3507-0	54	92	A	6500	Triode No. 2
6FY8	6.3	EV-3672-0	22	89	A	5700	Pent. Sect.
6FY8	6.3	EV-1908-0	21	62	A	1400	Triode Sect.
6G11‡	6.3	B3-8AX9-0	19	89	A	5500	Pent. No. 1
6G11	6.3	B3-3672-4	10	8	A	700	Pent. No. 2
6GA7‡	6.3	B3-4735-0	58	89	A	4500	Pent. Sect.
6GA7	6.3	B3-0A08-0	0	85	D	.....	Diode Sect.
6GB5	6.3	EV-2X78-0	64	89	A	5000	USE ADAPTER SA-8, 1050-168
6GC5	6.3	EV-6917-0	11	91	B	7500	
6GE5‡	6.3	B3-A72X-0	48	90	A	6000	
6GE8	6.3	EV-8917-0	14	72	A	1850	Pent. Sect.
6GE8	6.3	EV-3602-0	64	86	A	4700	Triode Sect.
6GF5‡	6.3	B3-A72X-0	54	88	A	4800	
6GF7‡	6.3	EV-9801-0	19	35	A	700	TRIODE NO. 1 USE ADAPTER SA-4, 1050-144. NOTE 3
6GF7	6.3	EV-2603-0	63	86	A	4200	Triode No. 2
Model 6000 A: No Adapter Required.							
6GH8	6.3	EV-2637-0	11	82	A	3000	Pent. Sect.
6GH8	6.3	EV-9108-0	21	85	A	3900	Triode Sect.
6GJ5‡	6.3	EV-6X73-0	28	91	B	6600	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000 A: No Adapter Required.							

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.		NOTATIONS
6GJ7	6.3	EV-2671-0	11	86	A	3500	Pent. Sect.
6GJ7	6.3	EV-9803-0	30	90	A	4250	Triode Sect.
6GJ8	6.3	EV-2637-0	10	83	A	3000	Pent. Sect.
6GJ8	6.3	EV-9108-0	10	84	A	3200	Triode Sect.
6GK5	6.3	ET-2507-6	19	89	A	5200	
6GK6	6.3	EV-2781-3	10	90	A	5750	
6GL7	6.3	JX-4506-0	23	23	A	600	Triode No. 1
6GL7	6.3	JX-1203-0	57	90	A	6400	Triode No. 2
6GM5	6.3	EV-6917-0	10	89	A	5100	
6GM6	6.3	ET-1562-7	10	86	A	5000	
6GN8	6.3	EV-7986-0	10	90	A	6000	Pent. Sect.
6GN8	6.3	EV-2301-0	16	60	A	1300	Triode Sect.
6GQ7	6.3	EV-0809-0	0	80	C	.....	Diode No. 1
6GQ7	6.3	EV-0607-0	0	80	C	.....	Diode No. 2
6GQ7	6.3	EV-0201-0	0	80	C	.....	Diode No. 3
6GT5‡	6.3	EV-6973-0	28	91	B	6600	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000 A: No Adapter Required.							
6GU5	6.3	ET-1562-0	13	89	A	5500	
6GU7	6.3	EV-7608-0	30	75	A	2050	Triode No. 1
6GU7	6.3	EV-2103-0	30	75	A	2050	Triode No. 2
6GV5‡	6.3	B3-92A4-0	42	86	A	4500	DO NOT USE TESTER CAP CONNECTOR. JUMPER CAP TO PIN 2 OF THE OCTAL SOCKET
6GW6	6.3	HS-5X48-0	28	91	B	6600	
6GW8	6.3	EV-8637-0	10	89	A	5500	Pent. Sect.
6GW8	6.3	EV-1902-0	10	45	A	950	Triode Sect.
6GX6	6.3	ET-1562-7	12	67	A	1600	
6GX7	6.3	EV-2671-0	11	84	A	3200	Pent. Sect.
6GX7	6.3	EV-9801-0	18	89	A	4800	Triode Sect.
6GY5‡	6.3	B3-527X-0	30	92	B	9000	DO NOT USE TESTER CAP CONNECTOR. JUMPER CAP TO PIN 2 OF THE OCTAL SOCKET.
6GY6	6.3	ET-1562-7	14	61	A	1350	
6GY8	6.3	EV-0607-0	0	79	C	.....	Triode No. 1
6GY8	6.3	FU-3908-0	20	75	A	2250	Triode No. 2
6GY8	6.3	FU-1200-0	29	75	A	2250	Triode No. 3
6GZ5	6.3	ET-2761-0	20	86	A	4000	
6HA5	6.3	ET-1507-6	20	87	A	4600	
6HA6	6.3	EV-2761-3	10	90	A	6500	
6HB5‡	6.3	B3-A72X-0	57	89	A	5600	
6HB6	6.3	EV-2781-9	10	92	A	7500	
6HB7	6.3	EV-2671-0	10	79	A	3100	Pent. Sect.
6HB7	6.3	EV-9801-0	11	89	A	4500	Triode Sect.
6H-B25	6.3	EV-2X79-8	50	87	A	4500	USE ADAPTER SA-8, 1050-168
6HC8	6.3	EV-3672-0	15	88	A	5100	Pent. Sect.
6HC8	6.3	EV-1908-0	9	73	A	2000	Triode Sect.
6HD5‡	6.3	B3-A79X-0	54	89	A	6000	
6HD7	6.3	EV-2671-0	10	79	A	2800	Pent. Sect.
6HD7	6.3	EV-9803-0	15	90	A	7000	Triode Sect.
6HE5‡	6.3	B3-96XA-0	23	87	A	4500	
6HE7‡	6.3	B3-95A8-0	54	91	A	7000	Pent. Sect.
6HE7	6.3	B3-0204-0	0	86	C	.....	Diode Sect.

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.	NOTATIONS
6HF5‡	6.3	B3-92A4-0	75	88	A 4300	DO NOT USE TESTER CAP CONNECTOR. JUMPER CAP TO PIN 2 OF THE OCTAL SOCKET.
6HF8	6.3	EV-7986-0	10	88	A 4800	Pent. Sect.
6HF8	6.3	EV-2301-0	20	69	A 1700	Triode Sect.
6HG5	6.3	ET-1562-0	11	86	A 4100	
6HG8	6.3	EV-2893-0	10	84	A 3600	Pent. Sect.
6HG8	6.3	EV-6703-0	32	82	A 3200	Triode Sect.
6HJ5‡	6.3	B3-A792-X	54	90	A 6500	
6HJ7	6.3	EV-2671-0	10	89	A 4000	Pent. Sect.
6HJ7	6.3	EV-9803-0	20	91	A 4500	Triode Sect.
6HJ8	6.3	EV-2631-9	10	85	A 3500	Pent. Sect.
6HJ8	6.3	EV-0807-0	0	79	C	Diode Sect.
6HK5	6.3	ET-1502-0	19	88	A 5000	
6HL5	6.3	EV-2793-0	15	93	A 9500	
6HL8	6.3	EV-2637-0	10	87	A 4400	Pent. Sect.
6HL8	6.3	EV-9108-0	18	87	A 4400	Triode Sect.
6HM5	6.3	ET-1507-6	20	87	A 4600	
6HM6	6.3	EV-2781-9	11	87	A 4700	
6HQ5	6.3	ET-1507-6	20	87	A 4400	
6HR5	6.3	ET-1562-0	10	87	A 4500	
6HR6	6.3	ET-1567-2	10	84	A 3600	
6HS5‡	6.3	B3-2704-3	0	88	A 4500	
6HS6	6.3	ET-1567-2	14	82	A 3200	
6HS8	6.3	EV-7821-9	10	15	A 600	Pent. No. 1
6HS8	6.3	EV-7321-6	10	15	A 600	Pent. No. 2
6HT6	6.3	EV-2781-9	10	87	A 4600	
6HV5‡	6.3	B3-7204-3	0	82	C	
6HW8	6.3	EV-6X37-9	13	72	A 1900	
Make external connection from Pin 2 and 8 of octal socket to plate cap lead. Connect Pin 1 to Pin 7 in octal socket.						
6HZ5‡	6.3	B3-2704-3	0	88	A 4500	
6HZ6	6.3	ET-1562-7	10	65	A 1400	
6HZ8	6.3	EV-7986-0	16	88	A 5000	Pent. Sect.
6HZ8	6.3	EV-2301-0	18	76	A 2300	Triode Sect.
6J4	6.3	ET-1702-0	20	90	A 6000	
6J6	6.3	ET-5207-0	21	81	A 3000	Triode No. 1
6J6	6.3	ET-6107-0	21	81	A 3000	Triode No. 2
6J9‡	6.3	EV-780X-0	17	81	A 3000	Triode No. 1
6J9	6.3	EV-960X-0	17	81	A 3000	Triode No. 2
6J9	6.3	EV-2103-0	17	81	A 3000	Triode No. 3
6J10‡	6.3	B3-7468-5	6	27	B 700	Pent. No. 1
6J10	6.3	B3-A923-0	16	88	A 4350	Pent. No. 2
6J11‡	6.3	B3-A978-X	10	86	A 4000	Pent. No. 1
6J11	6.3	B3-5326-4	10	86	A 4000	Pent. No. 2
6JA5‡	6.3	B3-9634-0	55	88	A 5400	
6JB5‡	6.3	B3-96XA-0	51	71	A 1800	
6JB6‡	6.3	EV-2X13-8	28	91	B 6600	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000 A: No Adapter Required.						
6JB8	6.3	EV-2637-0	25	45	A 1000	Pent. Sect.
6JB8	6.3	EV-9108-0	19	77	A 2400	Triode Sect.
6JC5‡	6.3	B3-96XA-0	23	87	A 4500	

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.	NOTATIONS
6JC6	6.3	EV-2781-9	11	88	A 5000	
6JC8	6.3	EV-2637-0	10	82	A 3000	Pent. Sect.
6JC8	6.3	EV-8901-0	10	89	A 5000	Triode Sect.
6JD5‡	6.3	B3-2704-3	0	88	A 4500	
6JD6	6.3	EV-2781-9	10	83	A 3200	
6JE6‡	6.3	EV-2X73-8	39	92	B 8100	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000 A: No Adapter Required.						
6JE8	6.3	EV-7986-0	11	89	A 5000	Pent. Sect.
6JE8	6.3	EV-2301-0	12	75	A 2200	Triode Sect.
6JF6‡	6.3	EV-2X73-8	32	92	B 7800	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000 A: No Adapter Required.						
6JF8	6.3	HR-5X46-0	25	90	B 6050	Pent. Sect.
6JF8	6.3	HR-0802-0	0	85	D	Diode Sect.
6JG5	6.3	EV-7986-0	10	90	A 6000	
6JG6‡	6.3	EV-2973-6	32	92	B 7800	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000 A: No Adapter Required.						
6JH5‡	6.3	B3-2704-3	0	88	A 4500	
6JH6	6.3	ET-1562-7	11	84	A 3700	
6JH8	6.3	EV-6937-1	23	57	A 1200	PLATE NO. 1. DISREGARD NEON FLASH IN SHORT TESTING.
6JH8	6.3	EV-6837-1	23	57	A 1200	PLATE NO. 2. DISREGARD NEON FLASH IN SHORT TESTING.
6JK5‡	6.3	B3-2704-3	0	88	A 4500	
6JK6	6.3	ET-1562-7	10	86	A 4800	
6JK8	6.3	EV-7608-9	23	78	A 2000	Triode No. 1
6JK8	6.3	EV-2103-9	20	89	A 5000	Triode No. 2
6JL6	6.3	ET-1562-7	16	85	A 4200	
6JL8	6.3	EV-7986-0	10	88	A 5200	Pent. Sect.
6JL8	6.3	EV-2301-0	17	81	A 2900	Triode Sect.
6JM6‡	6.3	B3-5632-4	43	88	A 7000	CONNECT JUMPER FROM TUBE CAP TO PIN NO. 6 ON OCTAL SOCKET.
6JN6‡	6.3	B3-A732-4	43	88	A 7000	
6JN8	6.3	EV-9678-0	10	82	A 3200	Pent. Sect.
6JN8	6.3	EV-1203-0	17	89	A 5500	Triode Sect.
6JQ6	6.3	EV-7139-6	50	85	A 3800	Pent. Sect.
6JQ6	6.3	EV-0609-0	0	70	C	Diode Sect.
6JR6‡	6.3	EV-2913-6	65	85	A 4200	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000A: No adapter required.						
6JS6A‡	6.3	B3-5632-4	53	88	A 4300	CONNECT JUMPER FROM TUBE CAP TO PIN NO. 6 ON OCTAL SOCKET.
6JT6‡	6.3	EV-2973-6	44	91	A 7000	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000 A: No Adapter Required.						
6JT8	6.3	EV-7986-0	12	90	A 6000	Pent. Sect.
6JT8	6.3	EV-2301-0	18	46	A 950	Triode Sect.
6JU6‡	6.3	EV-2X13-8	72	85	A 4200	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000 A: No Adapter Required.						
6JU8	6.3	EV-0809-0	0	78	C	Diode No. 1
6JU8	6.3	EV-0708-0	0	78	C	Diode No. 2
6JU8	6.3	EV-0203-0	0	78	C	Diode No. 3
6JU8	6.3	EV-0102-0	0	78	C	Diode No. 4

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.	NOTATIONS
6JV6‡	6.3	B3-A732-X	55	91	A 7000	
6JW8	6.3	EV-2637-0	17	87	A 2200	Pent. Sect.
6JW8	6.3	EV-9108-0	19	66	A 1600	Triode Sect.
6JV8	6.3	EV-7986-0	7	89	A 3700	Pent. Sect.
6JV8	6.3	EV-2301-0	20	69	A 1680	Triode Sect.
6JY8	6.3	EV-7986-0	18	86	A 4500	Pent. Sect.
6JY8	6.3	EV-2301-0	18	86	A 5000	Triode Sect.
6JZ6‡	6.3	B3-5632-4	56	91	A 7000	CONNECT A JUMPER FROM CAP TO PIN 6 OF OCTAL SOCKET
6JZ8‡	6.3	B3-7489-0	25	88	A 3900	Pent. Sect.
6JZ8	6.3	B3-X20A-0	29	65	A 1350	Triode Sect.
6K6	6.3	HS-5348-0	34	67	A 1600	
6K11‡	6.3	B3-9X04-8	24	75	A 2200	Triode No. 1
6K11	6.3	B3-7506-8	12	58	A 1250	Triode No. 2
6K11	6.3	B3-A203-8	12	58	A 1250	Triode No. 3
6KA8	6.3	EV-6983-7	16	70	A 1800	Pent. Sect.
6KA8	6.3	EV-2103-0	19	73	A 2000	Triode Sect.
6KD6‡	6.3	B3-5632-4	70	90	A 7500	CONNECT JUMPER FROM TUBE CAP TO PIN 6 ON OCTAL SOCKET.
6KD8	6.3	EV-2637-0	10	79	A 2600	Pent. Sect.
6KD8	6.3	EV-9108-0	19	89	A 5200	Triode Sect.
6KE8	6.3	EV-2637-0	11	85	A 3700	Pent. Sect.
6KE8	6.3	EV-9108-0	20	87	A 4500	Triode Sect.
6KF8	6.3	EV-7821-9	10	17	A 700	Pent. No. 1
6KF8	6.3	EV-7321-6	10	17	A 700	Pent. No. 2
6KL8	6.3	EV-2763-1	5	71	B 1700	Pent. Sect.
6KL8	6.3	EV-0803-0	0	33	C ------	DIODE SECT.
6KM6‡	6.3	EV-2X73-8	65	89	A 5000	OK ABOVE DIODES OK USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000 A: No Adapter Required.						
6KM8	6.3	EV-7986-0	5	50	B 950	TETRODE PLATE NO. 1
6KM8	6.3	EV-7286-0	5	53	B 1000	TETRODE PLATE NO. 2
6KM8	6.3	EV-7186-0	5	53	B 1000	TETRODE PLATE NO. 3
6KM8	6.3	EV-0306-0	0	35	C ------	DIODE SECT.
6KN6‡	6.3	B3-5632-4	60	88	A 4500	OK ABOVE DIODES OK DO NOT USE TESTER CAP CONNECTOR. JUMPER CAP TO PIN 6 OF OCTAL SOCKET
6KN8	6.3	EV-7608-0	22	90	A 6000	Triode No. 1
6KN8	6.3	EV-2103-0	22	90	A 6000	Triode No. 2
6KR8	6.3	EV-7986-0	14	91	A 4750	Pent. Sect.
6KR8	6.3	EV-2301-0	17	91	B 3900	Triode Sect.
6KS6	6.3	ET-2751-6	6	27	B 700	Limiter Grid
6KS6	6.3	ET-6751-2	13	0	B 500	Quadrature Grid
6KS8	6.3	EV-7986-0	16	87	A 4500	Pent. Sect.
6KS8	6.3	EV-2301-0	20	69	A 1700	Triode Sect.
6KT6	6.3	EV-2781-9	15	81	A 2350	
6KT8	6.3	EV-7986-0	10	85	A 4000	Pent. Sect.
6KT8	6.3	EV-2301-0	20	29	A 1700	Triode Sect.
6KU8	6.3	EV-7986-0	14	90	A 5500	Pent. Sect.
6KU8	6.3	EV-0301-0	0	26	C ------	Diode No. 1
6KU8	6.3	EV-0201-0	0	26	C ------	Diode No. 2
6KV6‡	6.3	EV-2973-6	41	87	B 4800	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000A: No Adapter Required.						

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.	NOTATIONS
6KV8	6.3	EV-7986-0	11	91	A 7400	Pent. Sect.
6KV8	6.3	EV-2301-0	19	72	A 1900	Triode Sect.
6KX8	6.3	EV-9708-6	12	58	A 1250	Triode No. 1
6KX8	6.3	EV-1302-6	12	58	A 1250	Triode No. 2
6KY6	6.3	EV-2781-3	17	88	A 5000	
6KY8‡	6.3	EV-2673-0	41	88	A 5000	PENT. SECT. USE ADAPTER SA-4, 1050-144. NOTE 3
6KY8	6.3	EV-9801-0	22	15	A 600	Triode Sect.
Model 6000 A: No Adapter Required.						
6KZ8	6.3	EV-2673-0	12	82	A 3200	Pent. Sect.
6KZ8	6.3	EV-9108-0	22	84	A 3600	Triode Sect.
6L6	6.3	HS-5348-1	17	88	A 5000	
6LB6‡	6.3	B3-5632-4	36	91	B 9650	CAP-P. CONNECT CAP OF TUBE TO PIN 6 OF OCTAL SOCKET
6LB8	6.3	EV-7986-0	14	89	A 5300	Pent. Sect.
6LB8	6.3	EV-2301-0	17	84	A 3600	Triode Sect.
6LC6	6.3	HS-0506-1	0	45	C ------	
6LC8	6.3	EV-6987-3	16	70	A 1800	Pent. Sect.
6LC8	6.3	EV-2103-0	19	73	A 2000	Triode Sect.
6LD6	6.3	EV-2781-9	12	86	B 4600	
6LE8	6.3	EV-9683-7	10	65	A 1500	Pent. No. 1
6LE8	6.3	EV-9183-2	10	65	A 1500	Pent. No. 2
6LF8	6.3	EV-7986-0	5	90	A 3500	Pent. Sect.
6LF8	6.3	EV-2301-0	19	64	A 1350	Triode Sect.
6LG6‡	6.3	B3-58A4-0	64	86	A 4650	CONNECT CAP OF TUBE TO PIN 8 OF OCTAL SOCKET
6LH6	6.3	HS-0506-1	0	45	C ------	
6LJ6	6.3	HS-0506-3	0	45	C ------	
6LJ8	6.3	EV-9678-0	15	75	A 2700	Pent. Sect.
6LJ8	6.3	EV-1203-0	24	75	A 2500	Triode Sect.
6LM8	6.3	EV-2637-0	13	82	A 3000	Pent. Sect.
6LM8	6.3	EV-9108-0	18	88	A 4700	Triode Sect.
6LN8	6.3	EV-2637-1	12	81	A 3000	Pent. Sect.
6LN8	6.3	EV-9108-6	26	85	A 4000	Triode Sect.
6LQ6‡	6.3	EV-2X73-8	39	92	B 8100	USE ADAPTER SA-4 1050-144. NOTE 3
Model 6000A: No Adapter Required.						
6LQ8	6.3	EV-7986-0	11	91	A 7400	Pent. Sect.
6LQ8	6.3	EV-2301-0	17	90	A 6500	Triode Sect.
6LR6‡	6.3	B3-5832-4	85	73	A 2250	CONNECT JUMPER FROM TUBE CAP TO PIN 6 ON OCTAL SOCKET.
6LR8‡	6.3	EV-2673-0	40	87	A 4000	PENT. SECT. USE ADAPTER SA-4, 1050-144. NOTE 3
6LR8	6.3	EV-9801-0	24	62	A 1400	Triode Sect.
Model 6000 A: No Adapter Required.						
6LT8	6.3	EV-9321-0	10	85	A 3700	Pent. Sect.
6LT8	6.3	EV-0807-0	0	92	D ------	Diode No. 1
6LT8	6.3	EV-0607-0	0	92	D ------	Diode No. 2
6LU6	6.3	ET-1562-7	11	86	A 4200	
6LU8‡	6.3	B3-6489-0	40	87	A 4000	Pent. Sect.
6LU8	6.3	B3-X20A-0	24	62	A 1400	Triode Sect.
						CONNECT JUMPER FROM

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.		NOTATIONS
6LU8‡	6.3	B3-6489-0	40	87	A	4000	Pent. Sect.
6LU8	6.3	B3-X20A-0	24	62	A	1400	Triode Sect.
6LV6‡	6.3	B3-5632-4	69	85	A	4350	CONNECT JUMPER FROM TUBE CAP TO PIN 6 ON OCTAL SOCKET
6LW6	6.3	HY-5X32-0	75	88	A	5500	
6LX6‡	6.3	B3-5632-4	70	90	A	7500	CONNECT JUMPER FROM TUBE CAP TO PIN 6 ON OCTAL SOCKET
6LY8	6.3	EV-7986-0	22	85	A	3400	Pent. Sect.
6LY8	6.3	EV-2301-0	17	48	A	1100	Triode Sect.
6LZ6‡	6.3	EV-6X73-8	75	88	A	4500	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000A: No Adapter Required.							
6M3	6.3	JS-030X-0	0	91	D	------	
6M11‡	6.3	B3-2A3X-0	11	86	A	3750	Pent. Sect.
6M11	6.3	B3-8709-0	20	82	A	3000	Triode No. 1
6M11	6.3	B3-5604-0	20	82	A	3000	Triode No. 2
6MA6	6.3	DY-4607-X	0	45	C	------	
6MB6‡	6.3	B3-5632-4	70	90	A	7500	CONNECT JUMPER FROM TUBE CAP TO PIN 6 ON OCTAL SOCKET
6MB8	6.3	EV-9678-0	8	84	A	4000	Pent. Sect.
6MB8	6.3	EV-1203-0	13	88	A	4800	Triode Sect.
6MC6‡	6.3	EV-2X73-8	70	90	A	7500	USE ADAPTER SA-4 1050-144. NOTE 3
Model 6000A: No Adapter Required.							
6MD8‡	6.3	EV-6307-0	20	85	A	3500	TRIODE NO. 1 USE ADAPTER SA-4, 1050-144. NOTE 3
6MD8	6.3	EV-8207-0	20	85	A	3500	Triode No. 2
6MD8	6.3	EV-9107-0	20	85	A	3500	Triode No. 3
Model 6000 A: No Adapter Required.							
6ME6‡	6.3	EV-2X73-8	39	92	B	8100	USE ADAPTER SA-4 1050-144. NOTE 3
Model 6000A: No Adapter Required.							
6ME8	6.3	EV-6937-2	24	25	A	700	Plate No. 1
6ME8	6.3	EV-6837-2	24	25	A	700	Plate No. 2
6MF8‡	6.3	B3-7489-0	30	84	A	4000	Pent. Sect.
6MF8	6.3	B3-X20A-0	23	66	A	1900	Triode Sect.
6MG8	6.3	EV-2637-0	10	81	A	3000	Pent. Sect.
6MG8	6.3	EV-9108-0	10	88	A	5000	Triode Sect.
6MH6‡	6.3	B3-5632-4	70	90	A	7500	CONNECT JUMPER FROM TUBE CAP TO PIN 6 ON OCTAL SOCKET. NOTE 3
Model 6000A: No Adapter Required.							
6MJ8‡	6.3	B3-A203-0	27	78	A	2800	Triode No. 1
6MJ8	6.3	B3-X403-0	27	78	A	2800	Triode No. 2
6MJ8	6.3	B3-8603-0	27	78	A	2800	Triode No. 3
6MK8	6.3	EV-7821-9	11	30	F	------	Pent. No. 1
6MK8	6.3	EV-7321-6	11	30	F	------	Pent. No. 2
6ML8	6.3	EV-6307-0	20	84	A	4000	Triode No. 1
6ML8	6.3	EV-8207-0	20	84	A	4000	Triode No. 3
6ML8	6.3	EV-9107-0	20	84	A	4000	Triode No. 3
6MN8‡	6.3	B3-8603-0	25	68	A	1850	Triode No. 1
6MN8	6.3	B3-X403-0	25	68	A	1850	Triode No. 2
6MN8	6.3	B3-A203-0	25	68	A	1850	Triode No. 3
6MQ8	6.3	EV-2637-0	15	80	A	3000	Pent. Sect.
6MQ8	6.3	EV-9108-0	20	83	A	3300	Triode Sect.
6MU8	6.3	EV-2637-0	19	86	A	4900	Pent. Sect.
6MU8	6.3	EV-9108-0	25	73	A	2400	Triode Sect.

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.		NOTATIONS
6MV8	6.3	EV-7986-0	10	86	A	4600	Pent. Sect.
6MV8	6.3	EV-2301-0	15	73	A	2200	Trioe Sect.
6MY8‡	6.3	B3-6489-0	40	87	A	4000	Pent. Sect.
6MY8	6.3	B3-X20A-0	24	62	A	1400	Triode Sect.
6Q11‡	6.3	B3-9X04-8	24	75	A	2200	Triode No. 1
6Q11	6.3	B3-7506-8	12	58	A	1250	Triode No. 2
6Q11	6.3	B3-A203-8	12	58	A	1250	•Triode No. 3
6R4	6.3	EV-1803-0	24	85	A	4000	
6S4	6.3	EV-6902-0	22	86	A	4150	
6SN7	6.3	HY-4506-0	23	79	A	2600	Triode No. 1
6SN7	6.3	HY-1203-0	23	79	A	2600	Triode No. 2
6T4	6.3	ET-2105-0	36	88	A	5000	
6T8	6.3	EV-8907-0	11	56	A	1200	Triode Sect.
6T8	6.3	EV-0607-0	0	77	C	------	Diode No. 1
6T8	6.3	EV-0203-0	0	77	C	------	Diode No. 2
6T8	6.3	EV-0107-0	0	77	C	------	Diode No. 3
6T9‡	6.3	B3-8AX9-0	15	87	A	4500	Pent. Sect.
6T9	6.3	B3-4205-0	19	36	A	950	Triode Sect.
6T10‡	6.3	B3-8AX9-0	19	88	A	4500	Pent. No. 1
6T10	6.3	B3-3762-5	14	21	B	625	Pent. No. 2
6U8	6.3	EV-2637-0	11	73	A	2000	Pent. Sect.
6U8	6.3	EV-9108-0	12	90	A	6200	Triode Sect.
6U9‡	6.3	FW-3782-4	10	83	A	3300	PENT. SECT. USE ADAPTER SA-11, 1050-177 MODEL 6000, 6005 NOTE 3
6U9	6.3	FW-X901-0	29	81	A	3000	Triode Sect.
6U10‡	6.3	B3-9X04-0	26	74	A	1900	Triode No. 1
6U10	6.3	B3-7506-0	19	14	A	575	Triode No. 2
6U10	6.3	B3-A203-0	26	74	A	1900	Triode No. 3
6V3	6.3	EV-020X-0	0	88	D	------	
6V5	6.3	HY-5340-0	40	86	A	4100	
6V6	6.3	HS-5348-1	13	86	A	4100	
6V9‡	6.3	FW-3741-2	10	48	B	1000	HEPT. SECT. USE ADAPTER SA-11, 1050-177 MODEL 6000, 6005 NOTE 3
6V9	6.3	FW-8X09-0	22	81	A	3000	Triode Sect.
6W4	6.3	HY-0503-0	0	88	D	------	
6W6	6.3	HS-5348-0	11	91	B	7500	
6X4	6.3	ET-0607-1	0	40	D	------	Plate No. 1
6X4	6.3	ET-0107-6	0	40	D	------	Plate No. 2
6X5	6.3	HS-0508-1	0	50	D	------	Plate No. 1
6X5	6.3	HS-0308-1	0	50	D	------	Plate No. 2
6X8	6.3	EV-7986-1	12	81	A	3000	Pent. Sect.
6X8	6.3	EV-2306-1	20	84	A	3500	Triode Sect.
6X9‡	6.3	FW-3782-4	10	84	A	3600	PENT. SECT. USE ADAPTER SA-11, 1050-177 MODEL 6000, 6005 NOTE 3
6X9	6.3	FW-X901-0	12	81	A	3000	Triode Sect.
6Y9‡	6.3	FW-8X97-0	13	88	A	5000	PENT. NO. 1. USE ADAPTER SA-11, 1050-177 MODEL 6000, 6005 NOTE 3
6Y9	6.3	FW-1432-0	13	83	A	3300	Pent. No. 2
6Y10‡	6.3	B3-8AX9-0	20	86	A	4000	Pent. No. 1
6Y10	6.3	B3-3762-5	12	67	A	1600	Pent. No. 2

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.	NOTATIONS
6JV6‡	6.3	B3-A732-X	55	91	A 7000	
6JW8	6.3	EV-2637-0	17	87	A 2200	Pent. Sect.
6JW8	6.3	EV-9108-0	19	66	A 1600	Triode Sect.
6JV8	6.3	EV-7986-0	7	89	A 3700	Pent. Sect.
6JV8	6.3	EV-2301-0	20	69	A 1680	Triode Sect.
6JY8	6.3	EV-7986-0	18	86	A 4500	Pent. Sect.
6JY8	6.3	EV-2301-0	18	86	A 5000	Triode Sect.
6JZ6‡	6.3	B3-5632-4	56	91	A 7000	CONNECT A JUMPER FROM CAP TO PIN 6 OF OCTAL SOCKET
6JZ8‡	6.3	B3-7489-0	25	88	A 3900	Pent. Sect.
6JZ8	6.3	B3-X20A-0	29	65	A 1350	Triode Sect.
6K6	6.3	HS-5348-0	34	67	A 1600	
6K11‡	6.3	B3-9X04-8	24	75	A 2200	Triode No. 1
6K11	6.3	B3-7506-8	12	58	A 1250	Triode No. 2
6K11	6.3	B3-A203-8	12	58	A 1250	Triode No. 3
6KA8	6.3	EV-6983-7	16	70	A 1800	Pent. Sect.
6KA8	6.3	EV-2103-0	19	73	A 2000	Triode Sect.
6KD6‡	6.3	B3-5632-4	70	90	A 7500	CONNECT JUMPER FROM TUBE CAP TO PIN 6 ON OCTAL SOCKET.
6KD8	6.3	EV-2637-0	10	79	A 2600	Pent. Sect.
6KD8	6.3	EV-9108-0	19	89	A 5200	Triode Sect.
6KE8	6.3	EV-2637-0	11	85	A 3700	Pent. Sect.
6KE8	6.3	EV-9108-0	20	87	A 4500	Triode Sect.
6KF8	6.3	EV-7821-9	10	17	A 700	Pent. No. 1
6KF8	6.3	EV-7321-6	10	17	A 700	Pent. No. 2
6KL8	6.3	EV-2763-1	5	71	B 1700	Pent. Sect.
6KL8	6.3	EV-0803-0	0	33	C ------	DIODE SECT. OK ABOVE DIODES OK
6KM6‡	6.3	EV-2X73-8	65	89	A 5000	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000 A: No Adapter Required.						
6KM8	6.3	EV-7986-0	5	50	B 950	TETRODE PLATE NO. 1
6KM8	6.3	EV-7286-0	5	53	B 1000	TETRODE PLATE NO. 2
6KM8	6.3	EV-7186-0	5	53	B 1000	TETRODE PLATE NO. 3
6KM8	6.3	EV-0306-0	0	35	C ------	DIODE SECT. OK ABOVE DIODES OK
6KN6‡	6.3	B3-5632-4	60	88	A 4500	DO NOT USE TESTER CAP CONNECTOR. JUMPER CAP TO PIN 6 OF OCTAL SOCKET
6KN8	6.3	EV-7608-0	22	90	A 6000	Triode No. 1
6KN8	6.3	EV-2103-0	22	90	A 6000	Triode No. 2
6KR8	6.3	EV-7986-0	14	91	A 4750	Pent. Sect.
6KR8	6.3	EV-2301-0	17	91	B 3900	Triode Sect.
6KS6	6.3	ET-2751-6	6	27	B 700	Limiter Grid
6KS6	6.3	ET-6751-2	13	0	B 500	Quadrature Grid
6KS8	6.3	EV-7986-0	16	87	A 4500	Pent. Sect.
6KS8	6.3	EV-2301-0	20	69	A 1700	Triode Sect.
6KT6	6.3	EV-2781-9	15	81	A 2350	
6KT8	6.3	EV-7986-0	10	85	A 4000	Pent. Sect.
6KT8	6.3	EV-2301-0	20	29	A 1700	Triode Sect.
6KU8	6.3	EV-7986-0	14	90	A 5500	Pent. Sect.
6KU8	6.3	EV-0301-0	0	26	C ------	Diode No. 1
6KU8	6.3	EV-0201-0	0	26	C ------	Diode No. 2
6KV6‡	6.3	EV-2973-6	41	87	B 4800	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000A: No Adapter Required.						
6KV8	6.3	EV-7986-0	11	91	A 7400	Pent. Sect.
6KV8	6.3	EV-2301-0	19	72	A 1900	Triode Sect.
6KX8	6.3	EV-9708-6	12	58	A 1250	Triode No. 1
6KX8	6.3	EV-1302-6	12	58	A 1250	Triode No. 2
6KY6	6.3	EV-2781-3	17	88	A 5000	
6KY8‡	6.3	EV-2673-0	41	88	A 5000	PENT. SECT. USE ADAPTER SA-4, 1050-144. NOTE 3
6KY8	6.3	EV-9801-0	22	15	A 600	Triode Sect.
Model 6000 A: No Adapter Required.						
6KZ8	6.3	EV-2673-0	12	82	A 3200	Pent. Sect.
6KZ8	6.3	EV-9108-0	22	84	A 3600	Triode Sect.
6L6	6.3	HS-5348-1	17	88	A 5000	
6LB6‡	6.3	B3-5632-4	36	91	B 9650	CAP=P. CONNECT CAP OF TUBE TO PIN 6 OF OCTAL SOCKET
6LB8	6.3	EV-7986-0	14	89	A 5300	Pent. Sect.
6LB8	6.3	EV-2301-0	17	84	A 3600	Triode Sect.
6LC6	6.3	HS-0506-1	0	45	C ------	
6LC8	6.3	EV-6987-3	16	70	A 1800	Pent. Sect.
6LC8	6.3	EV-2103-0	19	73	A 2000	Triode Sect.
6LD6	6.3	EV-2781-9	12	86	B 4600	
6LE8	6.3	EV-9683-7	10	65	A 1500	Pent. No. 1
6LE8	6.3	EV-9183-2	10	65	A 1500	Pent. No. 2
6LF8	6.3	EV-7986-0	5	90	A 3500	Pent. Sect.
6LF8	6.3	EV-2301-0	19	64	A 1350	Triode Sect.
6LG6‡	6.3	B3-58A4-0	64	86	A 4650	CONNECT CAP OF TUBE TO PIN 8 OF OCTAL SOCKET
6LH6	6.3	HS-0506-1	0	45	C ------	
6LJ6	6.3	HS-0506-3	0	45	C ------	
6LJ8	6.3	EV-9678-0	15	75	A 2700	Pent. Sect.
6LJ8	6.3	EV-1203-0	24	75	A 2500	Triode Sect.
6LM8	6.3	EV-2637-0	13	82	A 3000	Pent. Sect.
6LM8	6.3	EV-9108-0	18	88	A 4700	Triode Sect.
6LN8	6.3	EV-2637-1	12	81	A 3000	Pent. Sect.
6LN8	6.3	EV-9108-6	26	85	A 4000	Triode Sect.
6LQ6‡	6.3	EV-2X73-8	39	92	B 8100	USE ADAPTER SA-4 1050-144. NOTE 3
Model 6000A: No Adapter Required.						
6LQ8	6.3	EV-7986-0	11	91	A 7400	Pent. Sect.
6LQ8	6.3	EV-2301-0	17	90	A 6500	Triode Sect.
6LR6‡	6.3	B3-5832-4	85	73	A 2250	CONNECT JUMPER FROM TUBE CAP TO PIN 8 ON OCTAL SOCKET.
6LR8‡	6.3	EV-2673-0	40	87	A 4000	PENT. SECT. USE ADAPTER SA-4, 1050-144. NOTE 3
6LR8	6.3	EV-9801-0	24	62	A 1400	Triode Sect.
Model 6000 A: No Adapter Required.						
6LT8	6.3	EV-9321-0	10	85	A 3700	Pent. Sect.
6LT8	6.3	EV-0807-0	0	92	D ------	Diode No. 1
6LT8	6.3	EV-0607-0	0	92	D ------	Diode No. 2
6LU6	6.3	ET-1562-7	11	86	A 4200	
6LU8‡	6.3	B3-6489-0	40	87	A 4000	Pent. Sect.
6LU8	6.3	B3-X20A-0	24	62	A 1400	Triode Sect.
						CONNECT JUMPER FROM

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.		NOTATIONS
6LU8‡	6.3	B3-6489-0	40	87	A	4000	Pent. Sect.
6LU8	6.3	B3-X20A-0	24	62	A	1400	Triode Sect.
6LV6‡	6.3	B3-5632-4	69	85	A	4350	CONNECT JUMPER FROM TUBE CAP TO PIN 6 ON OCTAL SOCKET
6LW6	6.3	HY-5X32-0	75	88	A	5500	
6LX6‡	6.3	B3-5632-4	70	90	A	7500	CONNECT JUMPER FROM TUBE CAP TO PIN 6 ON OCTAL SOCKET
6LY8	6.3	EV-7986-0	22	85	A	3400	Pent. Sect.
6LY8	6.3	EV-2301-0	17	48	A	1100	Triode Sect.
6LZ6‡	6.3	EV-6X73-8	75	88	A	4500	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000A: No Adapter Required.							
6M3	6.3	JS-030X-0	0	91	D	------	
6M11‡	6.3	B3-2A3X-0	11	86	A	3750	Pent. Sect.
6M11	6.3	B3-8709-0	20	82	A	3000	Triode No. 1
6M11	6.3	B3-5604-0	20	82	A	3000	Triode No. 2
6MA6	6.3	DY-4607-X	0	45	C	------	
6MB6‡	6.3	B3-5632-4	70	90	A	7500	CONNECT JUMPER FROM TUBE CAP TO PIN 6 ON OCTAL SOCKET
6MB8	6.3	EV-9678-0	8	84	A	4000	Pent. Sect.
6MB8	6.3	EV-1203-0	13	88	A	4800	Triode Sect.
6MC6‡	6.3	EV-2X73-8	70	90	A	7500	USE ADAPTER SA-4 1050-144. NOTE 3
Model 6000A: No Adapter Required.							
6MD8‡	6.3	EV-6307-0	20	85	A	3500	TRIODE NO. 1 USE ADAPTER SA-4, 1050-144. NOTE 3
6MD8	6.3	EV-8207-0	20	85	A	3500	Triode No. 2
6MD8	6.3	EV-9107-0	20	85	A	3500	Triode No. 3
Model 6000 A: No Adapter Required.							
6ME6‡	6.3	EV-2X73-8	39	92	B	8100	USE ADAPTER SA-4 1050-144. NOTE 3
Model 6000A: No Adapter Required.							
6ME8	6.3	EV-6937-2	24	25	A	700	Plate No. 1
6ME8	6.3	EV-6837-2	24	25	A	700	Plate No. 2
6MF8‡	6.3	B3-7489-0	30	84	A	4000	Pent. Sect.
6MF8	6.3	B3-X20A-0	23	66	A	1900	Triode Sect.
6MG8	6.3	EV-2637-0	10	81	A	3000	Pent. Sect.
6MG8	6.3	EV-9108-0	10	88	A	5000	Triode Sect.
6MH6‡	6.3	B3-5632-4	70	90	A	7500	CONNECT JUMPER FROM TUBE CAP TO PIN 6 ON OCTAL SOCKET. NOTE 3
Model 6000A: No Adapter Required.							
6MJ8‡	6.3	B3-A203-0	27	78	A	2800	Triode No. 1
6MJ8	6.3	B3-X403-0	27	78	A	2800	Triode No. 2
6MJ8	6.3	B3-8603-0	27	78	A	2800	Triode No. 3
6MK8	6.3	EV-7821-9	11	30	F	------	Pent. No. 1
6MK8	6.3	EV-7321-6	11	30	F	------	Pent. No. 2
6ML8	6.3	EV-6307-0	20	84	A	4000	Triode No. 1
6ML8	6.3	EV-8207-0	20	84	A	4000	Triode No. 3
6ML8	6.3	EV-9107-0	20	84	A	4000	Triode No. 3
6MN8‡	6.3	B3-8603-0	25	68	A	1850	Triode No. 1
6MN8	6.3	B3-X403-0	25	68	A	1850	Triode No. 2
6MN8	6.3	B3-A203-0	25	68	A	1850	Triode No. 3
6MQ8	6.3	EV-2637-0	15	80	A	3000	Pent. Sect.
6MQ8	6.3	EV-9108-0	20	83	A	3300	Triode Sect.
6MU8	6.3	EV-2637-0	19	86	A	4900	Pent. Sect.
6MU8	6.3	EV-9108-0	25	73	A	2400	Triode Sect.

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.		NOTATIONS
6MV8	6.3	EV-7986-0	10	86	A	4600	Pent. Sect.
6MV8	6.3	EV-2301-0	15	73	A	2200	Trioe Sect.
6MY8‡	6.3	B3-6489-0	40	87	A	4000	Pent. Sect.
6MY8	6.3	B3-X20A-0	24	62	A	1400	Triode Sect.
6Q11‡	6.3	B3-9X04-8	24	75	A	2200	Triode No. 1
6Q11	6.3	B3-7506-8	12	58	A	1250	Triode No. 2
6Q11	6.3	B3-A203-8	12	58	A	1250	Triode No. 3
6R4	6.3	EV-1803-0	24	85	A	4000	
6S4	6.3	EV-6902-0	22	86	A	4150	
6SN7	6.3	HY-4506-0	23	79	A	2600	Triode No. 1
6SN7	6.3	HY-1203-0	23	79	A	2600	Triode No. 2
6T4	6.3	ET-2105-0	36	88	A	5000	
6T8	6.3	EV-8907-0	11	56	A	1200	Triode Sect.
6T8	6.3	EV-0607-0	0	77	C	------	Diode No. 1
6T8	6.3	EV-0203-0	0	77	C	------	Diode No. 2
6T8	6.3	EV-0107-0	0	77	C	------	Diode No. 3
6T9‡	6.3	B3-8AX9-0	15	87	A	4500	Pent. Sect.
6T9	6.3	B3-4205-0	19	36	A	950	Triode Sect.
6T10‡	6.3	B3-8AX9-0	19	88	A	4500	Pent. No. 1
6T10	6.3	B3-3762-5	14	21	B	625	Pent. No. 2
6U8	6.3	EV-2637-0	11	73	A	2000	Pent. Sect.
6U8	6.3	EV-9108-0	12	90	A	6200	Triode Sect.
6U9‡	6.3	FW-3782-4	10	83	A	3300	PENT. SECT. USE ADAPTER SA-11, 1050-177 MODEL 6000, 6005 NOTE 3
6U9	6.3	FW-X901-0	29	81	A	3000	Triode Sect.
6U10‡	6.3	B3-9X04-0	26	74	A	1900	Triode No. 1
6U10	6.3	B3-7506-0	19	14	A	575	Triode No. 2
6U10	6.3	B3-A203-0	26	74	A	1900	Triode No. 3
6V3	6.3	EV-020X-0	0	88	D	------	
6V5	6.3	HY-5340-0	40	86	A	4100	
6V6	6.3	HS-5348-1	13	86	A	4100	
6V9‡	6.3	FW-3741-2	10	48	B	1000	HEPT. SECT. USE ADAPTER SA-11, 1050-177 MODEL 6000, 6005 NOTE 3
6V9	6.3	FW-8X09-0	22	81	A	3000	Triode Sect.
6W4	6.3	HY-0503-0	0	88	D	------	
6W6	6.3	HS-5348-0	11	91	B	7500	
6X4	6.3	ET-0607-1	0	40	D	------	Plate No. 1
6X4	6.3	ET-0107-6	0	40	D	------	Plate No. 2
6X5	6.3	HS-0508-1	0	50	D	------	Plate No. 1
6X5	6.3	HS-0308-1	0	50	D	------	Plate No. 2
6X8	6.3	EV-7986-1	12	81	A	3000	Pent. Sect.
6X8	6.3	EV-2306-1	20	84	A	3500	Triode Sect.
6X9‡	6.3	FW-3782-4	10	84	A	3600	PENT. SECT. USE ADAPTER SA-11, 1050-177 MODEL 6000, 6005 NOTE 3
6X9	6.3	FW-X901-0	12	81	A	3000	Triode Sect.
6Y9‡	6.3	FW-8X97-0	13	88	A	5000	PENT. NO. 1. USE ADAPTER SA-11, 1050-177 MODEL 6000, 6005 NOTE 3
6Y9	6.3	FW-1432-0	13	83	A	3300	Pent. No. 2
6Y10‡	6.3	B3-8AX9-0	20	86	A	4000	Pent. No. 1
6Y10	6.3	B3-3762-5	12	67	A	1600	Pent. No. 2

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.		NOTATIONS
6Z4	6.3	FR-0304-0	0	60	D	.....	Plate No. 1
6Z4	6.3	FR-0204-0	0	60	D	.....	Plate No. 2
6Z10‡	6.3	B3-7468-5	6	27	B	700	Pent. No. 1
6Z10	6.3	B3-A923-0	16	88	A	4350	Pent. No. 2
7AU7	6.3	EV-7608-0	24	75	A	2200	Triode No. 1
7AU7	6.3	EV-2103-0	24	75	A	2200	Triode No. 2
7DJ8	7.5	EV-7608-0	22	91	A	7000	Triode No. 1
7DJ8	7.5	EV-2103-0	22	91	A	7000	Triode No. 2
7ES8	7.5	EV-7608-0	22	92	A	7500	Triode No. 1
7ES8	7.5	EV-2103-0	22	92	A	7500	Triode No. 2
7EY6	7.5	HS-5348-0	28	87	A	4400	
7FC7	7.5	EV-9608-0	24	90	A	5500	Triode No. 1
7FC7	7.5	EV-2301-0	24	90	A	5500	Triode No. 2
7HG8	7.5	EV-2893-0	10	84	A	3600	Pent. Sect.
7HG8	7.5	EV-6703-0	32	82	A	3200	Triode Sect.
7KY6	7.5	EV-2781-3	17	88	A	5000	
7KZ6	7.5	EV-2781-3	17	88	A	5000	
8AC9‡	7.5	B3-9AX8-7	10	87	A	4200	Pent. Sect.
8AC9	7.5	B3-0304-0	0	85	C	.....	Diode No. 1
8AC9	7.5	B3-0203-0	0	85	C	.....	Diode No. 2
8AC10‡	10.0	B3-9X04-0	10	80	A	3000	TRIODE NO. 1. MAKE "LINE TEST" AT 1240 ON 3000 SCALE.
8AC10	10.0	B3-7506-0	10	80	A	3000	Triode No. 2
8AC10	10.0	B3-A203-0	10	80	A	3000	Triode No. 3
8AL9‡	7.5	B3-A2X9-4	5	91	A	9000	Pent. Sect.
8AL9	7.5	B3-5706-0	9	88	A	6300	Triode Sect.
8AR11‡	7.5	B3-X89A-7	10	81	A	2700	Pent. No. 1
8AR11	7.5	B3-5236-4	10	81	A	2700	Pent. No. 2
8AU8	7.5	EV-7986-0	11	86	A	4200	Pent. Sect.
8AU8	7.5	EV-2301-0	15	86	A	4000	Triode Sect.
8AV11‡	7.5	B3-9X04-0	22	78	A	2500	Triode No. 1
8AV11	7.5	B3-7506-0	22	78	A	2500	Triode No. 2
8AV11	7.5	B3-A203-0	22	78	A	2500	Triode No. 3
8AW8A	7.5	EV-7986-0	10	88	A	5000	Pent. Sect.
8AW8A	7.5	EV-2301-0	15	78	A	2500	Triode Sect.
8B10‡	7.5	B3-5607-0	28	75	A	2000	TRIODE NO. 1 MAKE "LINE TEST" AT 1700 ON 3000 SCALE
8B10	7.5	B3-3402-0	28	75	A	2000	Triode No. 2
8B10	7.5	B3-0X09-0	0	76	C	.....	Diode No. 1
8B10	7.5	B3-0809-0	0	76	C	.....	Diode No. 2
8BA8A	7.5	EV-7986-0	11	88	A	5000	Pent. Sect.
8BA8A	7.5	EV-2301-0	30	79	A	2700	Triode Sect.
8BA11‡	7.5	B3-4638-7	10	15	A	600	Pent. No. 1
8BA11	7.5	B3-4238-5	10	15	A	600	Pent. No. 2
8BA11	7.5	B3-9A0X-0	30	62	A	1600	Triode Sect.
8BH8	7.5	EV-7986-0	7	88	A	5000	Pent. Sect.
8BH8	7.5	EV-2301-0	27	83	A	3000	Triode Sect.
8BM11‡	7.5	B3-A79X-8	10	85	A	3700	Pent. No. 1
8BM11	7.5	B3-6235-4	13	84	A	3500	Pent. No. 2

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.		NOTATIONS
8BN8	7.5	EV-8709-0	22	48	A	1000	Triode Sect.
8BN8	7.5	EV-0603-0	0	78	C	.....	Diode No. 1
8BN8	7.5	EV-0102-0	0	78	C	.....	Diode No. 2
8BN11‡	7.5	B3-7A98-X	10	85	A	3800	Pent. No. 1
8BN11	7.5	B3-3542-6	10	85	A	3800	Pent. No. 2
8BQ5	7.5	EV-2793-0	12	90	A	7500	
8BQ11‡	7.5	B3-X89A-7	5	85	A	4000	Pent. No. 1
8BQ11	7.5	B3-5236-4	5	89	A	5000	Pent. No. 2
8BU11‡	7.5	B3-8X9A-0	10	85	A	3800	Pent. Sect.
8BU11	7.5	B3-6705-0	15	89	A	5000	Triode No. 1
8BU11	7.5	B3-4302-0	15	89	A	5000	Triode No. 2
8CB11‡	7.5	B3-X89A-7	10	85	A	3700	Pent. No. 1
8CB11	7.5	B3-5236-4	10	85	A	3700	Pent. No. 2
8CG7	7.5	EV-7608-9	23	79	A	2600	Triode No. 1
8CG7	7.5	EV-2103-9	23	79	A	2600	Triode No. 2
8CM7	7.5	EV-7603-0	27	73	A	2000	Triode No. 1
8CM7	7.5	EV-8109-0	24	87	A	4400	Triode No. 2
8CN7	7.5	EV-7806-0	11	56	A	1200	Triode Sect.
8CN7	7.5	EV-0203-0	0	77	C	.....	Diode No. 1
8CN7	7.5	EV-0103-0	0	77	C	.....	Diode No. 2
8CS7	7.5	EV-7608-0	22	75	A	2200	Triode No. 1
8CS7	7.5	EV-3109-0	27	87	A	4500	Triode No. 2
8CW5	7.5	EV-2793-0	40	89	A	5500	
8CX8	7.5	EV-7986-0	16	83	A	3300	Pent. Sect.
8CX8	7.5	EV-2301-0	15	81	A	2900	Triode Sect.
8EB8	7.5	EV-7986-0	11	87	A	5100	Pent. Sect.
8EB8	7.5	EV-2301-0	11	70	A	2000	Triode Sect.
8EM5	7.5	EV-3917-0	12	89	A	4300	
8ET7	7.5	EV-7986-0	10	89	A	4750	Pent. Sect.
8ET7	7.5	EV-0301-0	0	21	C	.....	Diode No. 1
8ET7	7.5	EV-0201-0	0	21	C	.....	Diode No. 2
8FQ7	7.5	EV-7608-0	23	79	A	2600	Triode No. 1
8FQ7	7.5	EV-2103-0	23	79	A	2600	Triode No. 2
8GK6	7.5	EV-2781-3	10	90	A	5750	
8GN8	7.5	EV-7986-0	10	90	A	6000	Pent. Sect.
8GN8	7.5	EV-2301-0	16	60	A	1300	Triode Sect.
8GU7	7.5	EV-7608-0	30	75	A	2050	Triode No. 1
8GU7	7.5	EV-2103-0	30	75	A	2050	Triode No. 2
8GX7	7.5	EV-2671-0	11	84	A	3200	Pent. Sect.
8GX7	7.5	EV-9801-0	18	89	A	4800	Triode Sect.
8JL8	7.5	EV-7986-0	10	88	A	5200	Pent. Sect.
8JL8	7.5	EV-2301-0	17	81	A	2900	Triode Sect.
8JU8	7.5	EV-0809-0	0	78	C	.....	Diode No. 1
8JU8	7.5	EV-0708-0	0	78	C	.....	Diode No. 2
8JU8	7.5	EV-0203-0	0	78	C	.....	Diode No. 3
8JU8	7.5	EV-0102-0	0	78	C	.....	Diode No. 4
8JV8	7.5	EV-7986-0	7	89	A	3700	Pent. Sect.
8JV8	7.5	EV-2301-0	20	69	A	1680	Triode Sect.
8K11‡	7.5	B3-9X04-8	24	75	A	2200	Triode No. 1
8K11	7.5	B3-7506-8	12	58	A	1250	Triode No. 2
8K11	7.5	B3-A203-8	12	58	A	1250	Triode No. 3

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.		NOTATIONS
8KA8	7.5	EV-6983-7	16	70	A	1800	Pent. Sect.
8KA8	7.5	EV-2103-0	19	73	A	2000	Triode Sect.
8KR8	7.5	EV-7986-0	14	91	A	4750	Pent. Sect.
8KR8	7.5	EV-2301-0	17	91	A	3900	Triode Sect.
8LC8	7.5	EV-6987-3	16	70	A	1800	Pent. Sect.
8LC8	7.5	EV-2103-0	19	73	A	2000	Triode Sect.
8LR8‡	7.5	EV-2673-0	40	87	A	4000	PENT. SECT. USE ADAPTER SA-4, 1050-144 NOTE 3
8LR8	7.5	EV-9801-0	24	62	A	1400	Triode Sect.
Model 6000A: No Adapter Required.							
8LT8	7.5	EV-9321-6	10	85	A	3700	Pent. Sect.
8LT8	7.5	EV-0607-0	0	92	D	.....	Diode No. 1
8LT8	7.5	EV-0807-0	0	92	D	.....	Diode No. 2
8MU8	7.5	EV-2637-0	19	86	A	4900	Pent. Sect.
8MU8	7.5	EV-9108-0	25	73	A	2400	Triode Sect.
8U9‡	7.5	FW-3782-4	10	83	A	3300	PENT. SECT. USE ADAPTER SA-11, 1050-177. MODEL 6000,6005 NOTE 3
8U9	7.5	FW-X901-0	29	81	A	3000	Triode Sect.
8X9‡	7.5	FW-3782-4	10	84	A	3600	PENT. SECT. USE ADAPTER SA-11, 1050-177. MODEL 6000, 6005 NOTE 3
8X9	7.5	FW-X901-0	12	81	A	3000	Triode Sect.
9AH9‡	10.0	B3-5A87-9	10	87	A	5200	Pent. Sect.
9AH9	10.0	B3-2304-0	27	77	A	2350	Triode Sect.
9AK10‡	10.0	B3-9X04-0	14	85	A	4500	Triode No. 1
9AK10	10.0	B3-7506-0	14	85	A	4500	Triode No. 2
9AK10	10.0	B3-A203-0	14	85	A	4500	Triode No. 3
9AU7	10.0	EV-7608-0	24	75	A	2200	Triode No. 1
9AU7	10.0	EV-2103-0	24	75	A	2200	Triode No. 2
9BJ11‡	10.0	B3-A79X-8	10	66	A	1600	Pent. No. 1
9BJ11	10.0	B3-6235-4	13	84	A	3300	Pent. No. 2
9EA8	10.0	EV-2637-0	11	79	A	2600	Pent. Sect.
9EA8	10.0	EV-9108-0	11	89	A	5000	Triode Sect.
9GH8	10.0	EV-2637-0	11	82	A	3000	Pent. Sect.
9GH8	10.0	EV-9108-0	21	85	A	3900	Triode Sect.
9JW8	10.0	EV-2637-0	17	87	A	2200	Pent. Sect.
9JW8	10.0	EV-9108-0	19	66	A	1600	Triode Sect.
9KC6	7.5	EV-2791-6	10	85	A	3800	
9KX6	7.5	EV-2781-3	12	89	A	5500	
9KZ8	10.0	EV-2673-0	12	82	A	3200	Pent. Sect.
9KZ8	10.0	EV-9108-0	22	84	A	3600	Triode Sect.
9LA6	7.5	EV-2781-3	12	88	A	5000	
9ML8	10.0	EV-6307-0	20	84	A	4000	Triode No. 1
9ML8	10.0	EV-8207-0	20	84	A	4000	Triode No. 2
9ML8	10.0	EV-9107-0	20	84	A	4000	Triode No. 3
9MN8‡	10.0	B3-8603-0	25	68	A	1850	Triode No. 1
9MN8	10.0	B3-X403-0	25	68	A	1850	Triode No. 2
9MN8	10.0	B3-A203-0	25	68	A	1850	Triode No. 3
9R-AL1	10.0	EV-7608-0	33	58	A	1500	Triode No. 1
9R-AL1	10.0	EV-3109-0	35	79	A	3200	Triode No. 2

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.		NOTATIONS
9V9‡	10.0	FW-3741-2	10	48	B	1000	HEPT. SECT. USE ADAPTER SA-11, 1050-177. MODEL 6000, 6005 NOTE 3
9V9	10.0	FW-8X09-0	22	81	A	3000	Triode Sect.
10AL11‡	10.0	B3-8AX9-0	14	87	A	4300	Pent. No. 1
10AL11	10.0	B3-3672-4	20	21	A	620	Pent. No. 2
10BQ5	10.0	EV-2793-0	12	90	A	7500	
10CW5	10.0	EV-2793-0	40	89	A	5500	
10DE7	10.0	EV-7608-0	27	73	A	2000	Triode No. 1
10DE7	10.0	EV-2109-0	54	89	A	6500	Triode No. 2
10DR7	10.0	EV-7608-0	17	36	A	800	Triode No. 1
10DR7	10.0	EV-2109-0	56	88	A	3600	Triode No. 2
10EG7	10.0	HY-4506-0	30	73	A	2000	Triode No. 1
10EG7	10.0	HY-1203-0	50	92	A	7500	Triode No. 2
10EM7	10.0	HY-4506-0	10	66	A	1500	Triode No. 1
10EM7	10.0	HY-1203-0	53	91	A	5250	Triode No. 2
10GF7‡	10.0	EV-9801-0	19	35	A	700	TRIODE NO. 1 USE ADAPTER SA-4, 1050-144. NOTE 3
10GF7	10.0	EV-2603-0	63	86	A	4200	Triode No. 2
Model 6000 A: No Adapter Required.							
10GK6	10.0	EV-2781-3	10	90	A	5750	
10GN8	10.0	EV-7986-0	10	90	A	6000	Pent. Sect.
10GN8	10.0	EV-2301-0	16	60	A	1300	Triode Sect.
10GV8	10.0	EV-9678-0	28	91	A	6500	Pent. Sect.
10GV8	10.0	EV-2103-0	22	78	A	2200	Triode Sect.
10HF8	10.0	EV-7986-0	10	88	A	4800	Pent. Sect.
10HF8	10.0	EV-2301-0	20	69	A	1700	Triode Sect.
10J10‡	10.0	B3-7468-5	6	27	B	700	Pent. No. 1
10J10	10.0	B3-A923-0	16	88	A	4350	Pent. No. 2
10JA5‡	10.0	B3-9634-0	55	88	A	5400	
10JA8	10.0	EV-7986-0	11	89	A	5200	Tetrode Sect.
10JA8	10.0	EV-2301-0	22	71	A	1850	Triode Sect.
10JT8	10.0	EV-7986-0	12	90	A	6000	Pent. Sect.
10JT8	10.0	EV-2301-0	18	46	A	950	Triode Sect.
10JY8	10.0	EV-7986-0	18	86	A	4500	Pent. Sect.
10JY8	10.0	EV-2301-0	18	86	A	5000	Triode Sect.
10KR8	10.0	EV-7986-0	14	91	A	4750	Pent. Sect.
10KR8	10.0	EV-2301-0	17	91	B	3900	Triode Sect.
10KU8	10.0	EV-7986-0	14	90	A	5500	Pent. Sect.
10KU8	10.0	EV-0301-0	0	26	C	.....	Diode No. 1
10KU8	10.0	EV-0201-0	0	26	C	.....	Diode No. 2
10LB8	10.0	EV-7986-0	14	89	A	5300	Pent. Sect.
10LB8	10.0	EV-2301-0	17	84	A	3600	Triode Sect.
10LD6	10.0	EV-2781-3	12	86	B	4600	
10LE8	10.0	EV-9683-7	10	65	A	1500	Pent. No. 1
10LE8	10.0	EV-9183-2	10	65	A	1500	Pent. No. 2
10LW8	10.0	EV-7986-0	14	89	A	5000	Pent. Sect.
10LW8	10.0	EV-2301-0	22	59	A	1300	Triode Sect.
10LY8	10.0	EV-7986-0	22	85	A	3400	Pent. Sect.
10LY8	10.0	EV-2301-0	17	48	A	1100	Triode Sect.
10LZ8	10.0	EV-7986-0	14	87	A	4000	Pent. Sect.
10LZ8	10.0	EV-2301-0	21	0	A	500	Triode Sect.

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.		NOTATIONS
10T10‡	10.0	B3-8AX9-0	19	88	A	4500	Pent. No. 1
10T10	10.0	B3-3762-5	14	21	B	625	Pent. No. 2
10Z10‡	10.0	B3-7468-5	6	27	B	700	Pent. No. 1
10Z10	10.0	B3-A923-0	16	88	A	4350	Pent. No. 2
11AF9‡	12.6	FW-8X97-0	13	88	A	5000	PENT. NO. 1. USE ADAPTER SA-11, 1050-177 MODEL 6000, 6005. NOTE 3
11AF9	12.6	FW-1432-0	13	83	A	3300	Pent. No. 2
11AR11‡	10.0	B3-X89A-7	10	81	A	2700	Pent. No. 1
11AR11	10.0	B3-5236-4	10	81	A	2700	Pent. No. 2
11BQ11‡	12.6	B3-X89A-7	10	85	A	3500	PENT. NO. 1 MAKE "LINE TEST" AT 1400 ON 3000 SCALE
11BQ11	12.6	B3-5236-4	10	87	A	4000	Pent. No. 2
11BT11‡	10.0	B3-A2X8-6	13	89	A	6000	Pent. Sect.
11BT11	10.0	B3-5706-0	16	77	A	2800	Triode No. 1
11BT11	10.0	B3-3904-0	23	78	A	3000	Triode No. 2
11CA11‡	10.0	B3-8AX9-7	20	86	A	4250	Pent. Sect.
11CA11	10.0	B3-6405-0	20	73	A	2350	Triode No. 1
11CA11	10.0	B3-3207-0	20	75	A	2500	Triode No. 2
11CF11‡	10.0	B3-5346-0	5	91	A	8000	Pent. Sect.
11CF11	10.0	B3-9X08-0	5	86	A	4300	Triode No. 1
11CF11	10.0	B3-A207-0	5	89	A	5500	Triode No. 2
11CY7	10.0	EV-7608-0	10	53	A	1100	Triode No. 1
11CY7	10.0	EV-2109-0	60	86	A	4000	Triode No. 2
11DS5	12.6	ET-1562-0	13	87	A	4800	
11FY7‡	10.0	B3-XA09-0	20	32	A	800	Triode No. 1
11FY7	10.0	B3-3507-0	54	92	A	6500	Triode No. 2
11HM7	10.0	EV-2781-9	12	90	A	6000	
11JE8	10.0	EV-7986-0	11	89	A	5000	Pent. Sect.
11JE8	10.0	EV-2301-0	12	78	A	2200	Triode Sect.
11KV8	10.0	EV-7986-0	11	91	A	7400	Pent. Sect.
11KV8	10.0	EV-2301-0	19	72	A	1900	Triode Sect.
11LQ8	10.0	EV-7986-0	11	91	A	7400	Pent. Sect.
11LQ8	10.0	EV-2301-0	17	90	A	6500	Triode Sect.
11LT8	12.6	EV-9321-6	10	80	A	3200	PENT. SECT. MAKE "LINE TEST" AT 1400 ON 3000 SCALE
11LT8	12.6	EV-0607-0	0	81	D	------	Diode No. 1
11LT8	12.6	EV-0807-0	0	81	D	------	Diode No. 2
11LY6	10.0	EV-2781-3	11	87	A	4500	
11MS8	12.6	EV-9678-0	54	84	A	4400	Pent. Sect.
11MS8	12.6	EV-2103-0	22	74	A	2700	Triode Sect.
11Y9‡	10.0	FW-8X97-0	13	88	A	5000	PENT. NO. 1 USE ADAPTER SA-11, 1050-177. MODEL 6000, 6005 NOTE 3
11Y9	10.0	FW-1432-0	13	83	A	3300	Pent. No. 2
12AC10‡	12.6	B3-9X04-0	14	85	A	3700	Triode No. 1
12AC10	12.6	B3-7506-0	14	85	A	3700	Triode No. 2
12AC10	12.6	B3-A203-0	14	85	A	3700	Triode No. 3
12AE10‡	12.6	B3-8AX9-0	23	82	A	3200	Pent. No. 1
12AE10	12.6	B3-3762-5	22	35	A	800	Pent. No. 2
12AF3	12.6	EV-020X-0	0	80	D	------	
12AL5	12.6	ET-0701-6	0	78	C	------	Diode No. 1
12AL5	12.6	ET-0205-6	0	78	C	------	Diode No. 2

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.		NOTATIONS
12AL11‡	12.6	B3-8AX9-0	14	87	A	4300	Pent. No. 1
12AL11‡	12.6	B3-3672-4	20	21	A	620	Pent. No. 2
12AQ5	12.6	ET-1562-0	11	86	A	4100	
12AT6	12.6	ET-1702-0	10	60	A	1300	Triode Sect.
12AT6	12.6	ET-0602-0	0	26	C	------	Diode No. 1
12AT6	12.6	ET-0502-0	0	26	C	------	Diode No. 2
12AT7	12.6	EV-7608-0	11	82	A	3000	Triode No. 1
12AT7	12.6	EV-2103-0	11	82	A	3000	Triode No. 2
12AU6	12.6	ET-1567-2	11	76	A	2300	
12AU7	12.6	EV-7608-0	24	75	A	2200	Triode No. 1
12AU7	12.6	EV-2103-0	24	75	A	2200	Triode No. 2
12AV5	12.6	HS-1583-0	42	89	A	5500	
12AV6	12.6	ET-1702-5	12	58	A	1250	Triode Sect.
12AV6	12.6	ET-1602-0	0	26	C	------	Diode No. 1
12AV6	12.6	ET-1502-0	0	26	C	------	Diode No. 2
12AV7	12.6	EV-7608-2	20	85	A	4000	Triode No. 1
12AV7	12.6	EV-2103-7	20	85	A	4000	Triode No. 2
12AX3‡	12.6	B3-0407-0	0	82	D	------	
12AX7	12.6	EV-7608-0	12	58	A	1250	Triode No. 1
12AX7	12.6	EV-2103-0	12	58	A	1250	Triode No. 2
12AY3‡	12.6	EV-0209-0	0	87	D	------	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000 A: No Adapter Required.							
12AY7	12.6	EV-7608-0	18	58	A	1250	Triode No. 1
12AY7	12.6	EV-2103-0	18	58	A	1250	Triode No. 2
12AZ7	12.6	EV-7608-0	11	81	A	3000	Triode No. 1
12AZ7	12.6	EV-2103-0	11	81	A	3000	Triode No. 2
12B4	12.6	EV-2901-0	50	90	A	6500	
12BA6	12.6	ET-1567-2	11	72	A	1900	
12BA7	12.6	EV-7913-2	0	31	B	750	Ampl. Sect.
12BA7	12.6	EV-2103-7	16	88	A	5000	Osc. Sect.
12BD6	12.6	ET-1567-2	11	73	A	2000	
12BE3‡	12.6	B3-0X07-0	0	89	D	------	
12BE6	12.6	ET-7562-1	0	35	B	800	AMPL. SECT. MAKE NO GAS TEST
12BE6	12.6	ET-1602-7	20	90	A	6500	OSC. SECT. MAKE GAS TEST
12BF6	12.6	ET-1702-0	19	72	A	1900	Triode Sect.
12BF6	12.6	ET-0602-0	0	26	C	------	Diode No. 1
12BF6	12.6	ET-0502-0	0	26	C	------	Diode No. 2
12BF11‡	12.6	B3-8AX9-0	25	88	A	5000	Pent. No. 1
12BF11	12.6	B3-3762-5	13	7	A	550	Pent. No. 2
12BH7	12.6	EV-7608-2	32	77	A	2380	Triode No. 1
12BH7	12.6	EV-2103-7	32	77	A	2380	Triode No. 2
12BN6	12.6	ET-2751-6	6	27	B	700	Limiter Grid
12BN6	12.6	ET-6751-2	13	0	B	500	Quadrature Grid
12BQ6	12.6	HS-5X48-0	42	89	A	5500	
12BS3‡	12.6	EV-0209-0	0	83	D	------	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000 A: No Adapter Required.							
12BT3‡	12.6	B3-0407-0	0	88	D	------	
12BV11‡	12.6	B3-7X98-A	10	73	A	2000	Pent. No. 1
12BV11	12.6	B3-6345-2	10	73	A	2000	Pent. No. 2
12BY3	12.6	EV-020X-0	0	88	D	------	

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.		NOTATIONS
12BY7	12.6	EV-2781-3	11	87	A	4500	
12BZ6	12.6	ET-1562-7	11	81	A	3000	
12C5	12.6	ET-2761-0	20	91	B	7500	
12CA5	12.6	DU-2761-0	20	89	A	5500	
12CK3‡	12.6	EV-0209-0	0	86	C	.....	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000 A:	No Adapter Required.						
12CL3‡	12.6	EV-0209-0	0	86	C	.....	USE ADAPTER SA-4 1050-144. NOTE 3
Model 6000 A:	No Adapter Required.						
12CR6	12.6	ET-7561-2	14	74	A	2200	Pent. Sect.
12CR6	12.6	ET-0201-0	0	45	C	.....	Diode Sect.
12CS6	12.6	ET-1562-7	11	15	B	600	GRID NO. 1 MAKE GAS TEST
12CS6	12.6	ET-7562-1	0	31	B	750	GRID NO. 3 MAKE NO GAS TEST
12CT3	12.6	EV-0209-0	0	94	D	.....	OK ABOVE DIODES
12CU5	12.6	ET-2761-0	11	91	B	7000	
12CU6	12.6	HS-5X48-0	42	89	A	5500	
12D4	12.6	HY-0503-0	0	86	D	.....	
12DB5	12.6	EV-3912-0	11	91	B	7500	
12DJ8	12.6	EV-7608-0	22	91	A	7000	Triode No. 1
12DJ8	12.6	EV-2103-0	22	91	A	7000	Triode No. 2
12DM4	12.6	HY-0503-0	0	89	D	.....	
12DM5	12.6	ET-2761-0	20	91	B	7500	
12DQ6	12.6	HS-5X48-0	25	90	B	6000	
12DT5	12.6	EV-3917-0	21	87	A	4400	
12DT6	12.6	ET-1562-7	23	15	A	600	Grid No. 1
12DT6	12.6	ET-7562-1	16	0	B	500	Grid No. 3
12DT7	12.6	EV-7608-0	12	58	A	1250	Triode No. 1
12DT7	12.6	EV-2103-0	12	58	A	1250	Triode No. 2
12DT8	12.6	EV-7608-9	11	81	A	3000	Triode No. 1
12DT8	12.6	EV-2103-9	11	81	A	3000	Triode No.
12DW4	12.6	EV-0209-0	0	89	D	.....	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000A:	No Adapter Required.						
12DW7	12.6	EV-7608-0	12	58	A	1250	Triode No.
12DW7	12.6	EV-2103-0	25	75	A	2200	Triode No.
12FQ8	12.6	EV-7809-0	10	35	A	800	TRIODE NO. 1 PLATE NO. 1
12FQ8	12.6	EV-7609-0	10	35	A	800	TRIODE NO. 1 PLATE NO. 2
12FQ8	12.6	EV-2309-0	10	35	A	800	TRIODE NO. 2 PLATE NO. 1
12FQ8	12.6	EV-2109-0	10	35	A	800	TRIODE NO. 2 PLATE NO. 2
12FX5	12.6	ET-2761-0	10	90	A	5750	
12G11‡	12.6	B3-8AX9-0	19	89	A	5500	Pent. No. 1
12G11	12.6	B3-3672-4	10	8	A	700	Pent. No. 2
12GC6	12.6	HS-5X83-0	45	90	A	6000	
12GE5‡	12.6	B3-A72X-0	48	90	A	6000	
12GJ5‡	12.6	EV-6X73-0	28	91	B	6600	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000 A:	No Adapter Required.						
12GN7	12.6	EV-2781-9	12	89	A	5550	
12GT5‡	12.6	EV-6973-0	28	91	B	6600	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000 A:	No Adapter Required.						
12GV5‡	12.6	B3-92A4-0	42	86	A	4500	DO NOT USE TESTER CAP CONNECTOR. JUMPER CAP TO PIN 2 OF THE OCTAL SOCKET.

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.		NOTATIONS
							OCTAL SOCKET.
12GW6	12.6	HS-5X48-0	28	91	B	6600	
12H-B25	12.6	EV-2X79-8	50	87	A	4500	USE ADAPTER SA-8, 1050-198
12HE7‡	12.6	B3-95A8-0	54	91	A	7000	Pent. Sect.
12HE7	12.6	B3-0204-0	0	86	C	.....	Diode Sect.
12HG7	12.6	EV-2781-3	10	91	A	7500	
12HL5	12.6	EV-2793-0	15	93	A	9500	
12HL7	12.6	EV-2781-3	15	89	A	5000	
12JB6‡	12.6	EV-2X13-8	28	91	B	6600	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000 A:	No Adapter Required.						
12JF5‡	12.6	B3-3724-0	25	90	B	6000	CONNECT JUMPER FROM TUBE CAP TO PIN 7 ON OCTAL SOCKET
12JN6‡	12.6	B3-A732-4	43	88	A	7000	
12JN8	12.6	EV-9678-0	10	82	A	3200	Pent. Sect.
12JN8	12.6	EV-1203-0	17	89	A	5500	Triode Sect.
12JQ6	12.6	EV-7139-6	50	85	A	3800	Pent. Sect.
12JQ6	12.6	EV-0609-0	0	70	C	.....	Diode Sect.
12JS6‡	12.6	B3-5632-4	53	88	A	4300	CONNECT JUMPER FROM TUBE CAP TO PIN 6 ON OCTAL SOCKET
12JT6‡	12.6	EV-2973-6	44	91	A	7000	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000 A:	No Adapter Required.						
12K5	12.6	ET-2751-0	10	80	B	3000	
12MD8‡	12.6	EV-6307-0	20	85	A	3500	TRIODE NO. 1 USE ADAPTER SA-4, 1050-144. NOTE 3
12MD8	12.6	EV-8207-0	20	85	A	3500	Triode No. 2
12MD8	12.6	EV-9107-0	20	85	A	3500	Triode No. 3
Model 6000 A:	No Adapter Required.						
12MN8‡	12.6	B3-8603-0	25	68	A	1850	Triode No. 1
12MN8	12.6	B3-X403-0	25	68	A	1850	Triode No. 2
12MN8	12.6	B3-A203-0	25	68	A	1850	Triode No. 3
12R-LL5	12.6	EV-7608-0	23	79	A	2600	Triode No. 1
12R-LL5	12.6	EV-2103-0	23	79	A	2600	Triode No. 2
12SN7	12.6	HY-4506-0	23	79	A	2600	Triode No. 1
12SN7	12.6	HY-1203-0	23	79	A	2600	Triode No. 2
12T10‡	12.6	B3-8AX9-0	19	88	A	4500	Pent. No. 1
12T10	12.6	B3-3762-5	14	21	B	625	Pent. No. 2
12V6	12.6	HS-5348-0	13	86	A	4100	
12W6	12.6	HS-5348-0	11	91	B	7500	
12X4	12.6	ET-0607-1	0	40	D	.....	Plate No. 1
12X4	12.6	ET-0107-6	0	40	D	.....	Plate No. 2
13CW4‡	12.6	DR-4208-0	23	79	A	2600	USE ADAPTER SA-3, 1050-127. NOTE 3
Model 6000 A:							
13CW4	12.6	13-4208-0	23	79	A	2600	
13DE7	12.6	EV-7608-0	27	73	A	2000	Triode No. 1
13DE7	12.6	EV-2109-0	54	89	A	6500	Triode No. 2
13DR7	12.6	EV-7608-0	17	36	A	800	Triode No. 1
13DR7	12.6	EV-2109-0	56	88	A	3600	Triode No. 2
13EM7	12.6	HY-4506-0	10	66	A	1500	Triode No. 1
13EM7	12.6	HY-1203-0	53	91	A	5250	Triode No. 2
13FD7	12.6	EV-7608-0	10	68	A	1600	Triode No. 1
13FD7	12.6	EV-2109-0	58	89	A	4500	Triode No. 2

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.		NOTATIONS
13FM7‡	12.6	B3-XA09-0	20	46	A	950	Triode No. 1
13FM7	12.6	B3-8507-0	62	88	A	5250	Triode No. 2
13GF7‡	12.6	EV-9801-0	19	35	A	700	TRIODE NO. 1 USE ADAPTER SA-4, 1050-144. NOTE 3
13GF7	12.6	EV-2603-0	63	86	A	4200	Triode No. 2
Model 6000 A: No Adapter Required.							
13J10‡	12.6	B3-7468-5	6	27	B	700	Pent. No. 1
13J10	12.6	B3-A923-0	16	88	A	4350	Pent. No. 2
13JZ8‡	12.6	B3-7489-0	25	88	A	3900	Pent. Sect.
13JZ8	12.6	B3-X20A-0	29	65	A	1350	Triode Sect.
13V10‡	12.6	B3-8AX9-0	21	87	A	4200	Pent. No. 1
13V10	12.6	B3-3762-5	24	0	A	500	Pent. No. 2
13Z10‡	12.6	B3-7468-5	6	27	B	700	Pent. No. 1
13Z10	12.6	B3-A923-0	16	88	A	4350	Pent. No. 2
14BL11‡	12.6	B3-A2X8-0	13	90	A	5500	Pent. Sect.
14BL11	12.6	B3-5706-0	14	82	A	3000	Triode No. 1
14BL11	12.6	B3-3904-0	22	82	A	3000	Triode No. 2
14BR11‡	12.6	B3-2A34-0	10	89	A	4750	Pent. Sect.
14BR11	12.6	B3-8605-0	17	81	A	2600	Triode No. 1
14BR11	12.6	B3-X907-0	14	82	A	3000	Triode No. 2
14GT8	12.6	EV-8907-0	10	15	A	600	Triode Sect.
14GT8	12.6	EV-0601-0	0	80	C	.....	Diode No. 1
14GT8	12.6	EV-0203-0	0	80	C	.....	Diode No. 2
14JG8	12.6	EV-8907-0	10	65	A	1500	Triode Sect.
14JG8	12.6	EV-0601-0	0	77	C	.....	Diode No. 1
14JG8	12.6	EV-0203-0	0	77	C	.....	Diode No. 2
15AF11‡	17.0	B3-A2X9-0	8	90	A	5400	PENT. SECT. MAKE "LINE TEST" AT 1450 ON 3000 SCALE
15AF11	17.0	B3-6805-0	17	81	A	2700	Triode No. 1
15AF11	17.0	B3-3407-0	13	82	A	2800	Triode No. 2
15BD11‡	17.0	B3-A2X9-0	12	87	A	4500	PENT. SECT. MAKE "LINE TEST" AT 1400 ON 3000 SCALE
15BD11	17.0	B3-6805-0	13	78	A	2500	Triode No. 1
15BD11	17.0	B3-3407-0	10	80	A	2750	Triode No. 2
15CW5	17.0	EV-2793-0	42	88	A	5000	MAKE "LINE TEST" AT 1400 ON 3000 SCALE.
15EW7	17.0	EV-7608-0	30	63	A	1450	TRIODE NO. 1 MAKE "LINE TEST" AT 1400 ON 3000 SCALE
15EW7	17.0	EV-2109-0	56	91	A	4350	Triode No. 2
15FM7‡	12.6	B3-XA09-0	20	46	A	950	Triode No. 1
15FM7	12.6	B3-8507-0	59	88	A	5250	Triode No. 2
15FY7‡	17.0	B3-XA09-0	18	33	A	750	TRIODE NO. 1 MAKE "LINE TEST" AT 1450 ON 3000 SCALE
15FY7	17.0	B3-3507-0	47	91	A	6500	Triode No. 2
15HA6	17.0	EV-2761-3	10	90	A	6500	
15HB6	17.0	EV-2781-9	20	88	A	5000	
15KY8‡	17.0	EV-2673-0	42	80	A	2550	PENT. SECT. MAKE "LINE TEST" AT 1425 ON 3000 SCALE USE ADAPTER SA-4, 1050-144. NOTE 3
15KY8	17.0	EV-9801-0	19	27	A	700	Triode Sect.
Model 6000 A: No Adapter Required.							

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.		NOTATIONS
15LE8	12.6	EV-9683-7	10	57	A	1300	PENT. NO. 1. MAKE "LINE TEST" AT 1700 ON 3000 SCALE
15LE8	12.6	EV-9183-2	10	57	A	1300	Pent. No. 2
15MF8‡	12.6	B3-7489-0	30	84	A	4000	PENT. SECT. MAKE "LINE TEST" AT 1450 ON 3000 SCALE
15MF8	12.6	B3-X20A-0	23	66	A	1900	Triode Sect.
15MX8‡	17.0	EV-2673-0	42	80	A	2550	PENT. SECT. MAKE "LINE TEST" AT 1425 ON 3000 SCALE. USE ADAPTER SA-3 1050-144 NOTE 3.
15MX8	17.0	EV-9801-0	19	27	A	700	Triode Sect.
Model 6000A: No Adapter Required.							
16AK9‡	17.0	B3-8597-0	30	85	A	4150	Pent. Sect.
16AK9	17.0	B3-XA07-0	18	75	A	2400	Triode No. 1
16AK9	17.0	B3-3207-0	26	59	A	1750	Triode No. 2
16BQ11‡	17.0	B3-X89A-7	10	85	A	3500	Pent. No. 1
16BQ11	17.0	B3-5236-4	10	87	A	4000	Pent. No. 2
16BX11‡	17.0	B3-2A3X-0	5	88	A	4900	Pent. Sect.
16BX11	17.0	B3-8709-0	5	89	A	5500	Triode No. 1
16BX11	17.0	B3-5604-0	5	90	A	6000	Triode No. 2
16GK6	17.0	EV-2781-3	7	90	A	5900	
16GY5‡	17.0	B3-527X-0	30	92	B	9000	DO NOT USE TESTER CAP CONNECTOR. CONNECT CAP TO PIN 2 OF OCTAL SOCKET
16HB5‡	17.0	B3-A72X-0	57	89	A	5600	
16JV6‡	17.0	B3-A732-X	55	91	A	7000	
16KA6‡	17.0	B3-523X-4	57	89	A	5500	DO NOT USE TESTER CAP CONNECTER. CONEECT CAP TO PIN 2 OF N OCTAL SOCKET
16LU8‡	17.0	B3-6489-0	40	87	A	4000	Pent. Sect.
16LU8	17.0	B3-X20A-0	24	62	A	1400	Triode Sect.
16MY8‡	17.0	B3-6489-0	40	87	A	4000	Pent. Sect.
16MY8	17.0	B3-X20A-0	24	62	A	1400	Triode Sect.
16Y9‡	17.0	FW-8X97-0	13	88	A	5000	PENT. NO. 1. USE ADAPTER SA-11, 1050-177 MODEL 6060, 6005 NOTE 3
16Y9	17.0	FW-1432-0	13	83	A	3300	Pent. No. 2
17AB9‡	17.0	FW-978X-0	15	81	A	3000	TETRODE NO. 1. USE ADAPTER SA-11. 1050-177 MODEL 6000, 6005 NOTE 3
17AB9	17.0	FW-3124-0	15	81	A	3000	Tetrode No. 2
17AB10‡	17.0	B3-7468-5	6	27	B	700	Limiter Grid
17AB10	17.0	B3-5468-7	13	0	B	500	Quadrature Grid
17AB10	17.0	B3-A923-0	25	83	A	3100	Pent. No. 2
17AX3‡	17.0	B3-0407-0	0	82	D	.....	
17AX4	17.0	HY-0503-0	0	82	D	.....	
17AY3‡	17.0	EV-0209-0	0	87	D	.....	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000 A: No Adapter Required.							
17BE3‡	17.0	B3-0X07-0	0	89	D	.....	
17BF11‡	17.0	B3-8AX9-0	25	88	A	5000	Pent. No. 1
17BF11	17.0	B3-3762-5	13	7	A	540	Pent. No. 2
17BH3‡	17.0	EV-0209-0	0	87	D	.....	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000 A: No Adapter Required.							
17BQ6	17.0	HS-5X48-0	42	89	A	5500	
17BS3‡	17.0	EV-0209-0	0	83	D	.....	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000 A: No Adapter Required.							

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.		NOTATIONS
17BW3‡	17.0	B3-0407-0	0	89	D	.....	OK ABOVE DIODES OK
17BZ3‡	17.0	B3-0X07-0	0	86	C	.....	
17C5	17.0	ET-2761-0	20	91	B	7500	
17C9‡	17.0	EV-7986-0	15	85	A	3200	Tetrode No. 1
17C9	17.0	EV-132X-0	15	85	A	3200	Tetrode No. 2
17CK3‡	17.0	EV-0209-0	0	86	C	.....	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000 A: No Adapter Required.							
17CL3‡	17.0	EV-0209-0	0	86	C	.....	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000 A: No Adapter Required.							
17CT3	17.0	EV-0209-0	0	94	D	.....	OK ABOVE DIODES OK
17CU5	17.0	ET-2761-0	38	86	A	4300	
17D4	17.0	HY-0503-0	0	86	D	.....	
17DE4	17.0	HY-0503-0	0	89	D	.....	
17DM4	17.0	HY-0503-0	0	89	D	.....	
17DQ6	17.0	HS-5X48-0	25	90	B	6000	
17DW4	17.0	EV-0209-0	0	89	D	.....	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000A: No Adapter Required.							
17GE5‡	17.0	B3-A72X-0	48	90	A	6000	
17GJ5‡	17.0	EV-6X73-0	28	91	B	6600	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000 A: No Adapter Required.							
17GT5‡	17.0	EV-6973-0	28	91	B	6600	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000 A: No Adapter Required.							
17GV5‡	17.0	B3-92A4-0	44	91	A	7000	DO NOT USE TESTER CAP CONNECTOR. JUMPER CAP TO PIN 2 OF THE OCTAL SOCKET
17GW6	17.0	HS-5X48-0	28	91	B	6600	
17H3	17.0	EV-0301-0	0	80	D	.....	
17H-B25	17.0	EV-2X79-8	50	87	A	4500	USE ADAPTER SA-8, 1050-168
17JB6‡	17.0	EV-2X13-8	28	91	B	6600	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000 A: No Adapter Required.							
17JF6‡	17.0	EV-2X73-8	32	92	B	7800	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000 A: No Adapter Required							
17JG6A‡	17.0	EV-2973-6	32	92	B	7800	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000 A: No Adapter Required.							
17JM6‡	17.0	B3-5632-4	43	88	A	7000	CONNECT JUMPER FROM TUBE CAP TO PIN NO. 6 ON OCTAL SOCKET
17JN6‡	17.0	B3-A732-4	43	88	A	7000	
17JQ6	17.0	EV-7139-6	50	85	A	3800	Pent. Sect.
17JQ6	17.0	EV-0609-0	0	70	C	.....	Diode Sect.
17JR6‡	17.0	EV-2913-6	65	85	A	4200	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000A: No adapter required.							
17JT6‡	17.0	EV-2973-6	44	91	A	7000	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000 A: No Adapter Required.							
17JZ8‡	17.0	B3-7489-0	33	88	A	5000	Pent. Sect.
17JZ8	17.0	B3-X20A-0	31	57	A	1350	Triode Sect.
17KV6‡	17.0	EV-2973-6	41	87	B	4800	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000A: No Adapter Required.							
17LD8‡	17.0	EV-2673-0	35	91	A	4800	PENT. SECT. USE ADAPTER SA-4, 1050-144. NOTE 3
17LD8	17.0	EV-9801-0	31	73	A	1300	Triode Sect.
Model 6000 A: No Adapter Required.							

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.		NOTATIONS
17X10‡	17.0	B3-7468-5	6	27	B	700	Limiter Grid
17X10	17.0	B3-5468-7	13	0	B	500	QUADRATURE GRID
17X10	17.0	B3-A923-0	25	83	A	3100	Pent. No. 2
18A5	17.0	HS-1583-0	40	88	A	4800	
18AJ10‡	17.0	B3-8AX9-0	29	72	B	2400	Pent. No. 1
18AJ10	17.0	B3-3762-5	10	60	A	900	Pent. No. 2
18FW6	17.0	ET-1567-2	12	73	A	2000	
18FX6	17.0	ET-1562-7	11	43	A	900	Ampl. Sect.
18FX6	17.0	ET-1602-7	19	88	A	5000	Osc. Sect.
18FY6	17.0	ET-1702-0	21	0	A	.....	TRIODE SECT. OK ABOVE 900 ON 3000 SCALE.
18FY6	17.0	ET-0602-0	0	32	C	.....	Diode No. 1
18FY6	17.0	ET-0502-0	0	32	C	.....	Diode No. 2
18GB5	17.0	EV-2X78-0	64	89	A	5000	USE ADAPTER SA-8 1050-168
18GD6A	17.0	ET-1567-2	15	73	A	1750	
19AQ5	20.0	ET-1562-0	11	86	A	4100	
19AU4	20.0	HY-0503-0	0	89	D	.....	
19CG3‡	20.0	B3-0407-0	0	91	D	.....	
19CL8A	20.0	EV-9678-0	10	84	A	3300	Tetrode Sect.
19CL8A	20.0	EV-1203-0	12	89	A	6000	Triode Sect.
19DE3‡	20.0	B3-0403-0	0	86	C	.....	CONNECT JUMPER FROM TUBE CAP TO PIN 3 ON OCTAL SOCKET
19DK3	20.0	EV-020X-0	0	86	C	.....	
19DQ3‡	20.0	B3-0407-0	0	86	C	.....	
19EA8	20.0	EV-2637-0	17	79	A	2600	Pent. Sect.
19EA8	20.0	EV-9108-0	13	89	A	5000	Triode Sect.
19EZ8	20.0	EV-9800-0	19	69	A	1700	Triode No. 1
19EZ8	20.0	EV-7600-0	19	69	A	1700	Triode No. 2
19EZ8	20.0	EV-2301-0	20	71	A	1850	Triode No. 3
If no reading is obtained, use selector setting FU- in place of EV-.							
19FX5	20.0	ET-2761-0	10	90	A	5750	
19GQ7	20.0	EV-0809-0	0	80	C	.....	Diode No. 1
19GQ7	20.0	EV-0607-0	0	80	C	.....	Diode No. 2
19GQ7	20.0	EV-0201-0	0	80	C	.....	Diode No. 3
19HR6	20.0	ET-1567-2	10	84	A	3600	
19HS6	20.0	ET-1567-2	14	82	A	3200	
19HV8	20.0	EV-9678-0	11	81	A	3000	Pent. Sect.
19HV8	20.0	EV-1203-0	14	59	A	1300	Triode Sect.
19JN8	20.0	EV-9678-0	10	82	A	3200	Pent. Sect.
19JN8	20.0	EV-1203-0	17	89	A	5500	Triode Sect.
19KG8	20.0	EV-9678-0	11	82	A	3100	Pent. Sect.
19KG8	20.0	EV-2103-0	18	88	A	5100	Triode Sect.
19M-R9	17.0	ET-1567-2	15	73	A	1750	
19Q9‡	20.0	EV-132X-6	10	82	A	3100	Pent. Sect.
19Q9	20.0	EV-8907-6	18	87	A	4600	Triode Sect.
19X8	20.0	EV-7986-1	12	81	A	3000	Pent. Sect.
19X8	20.0	EV-2306-1	20	84	A	3500	Triode Sect.
20AQ3	20.0	EV-090X-0	0	93	D	.....	
20EW7	20.0	EV-7608-0	27	72	A	2000	Triode No. 1
20EW7	20.0	EV-2109-0	54	88	A	6000	Triode No. 2
20EZ7	20.0	CR-8709-0	12	58	A	1250	Triode No. 1
20EZ7	20.0	CR-5604-0	12	58	A	1250	Triode No. 2

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.		NOTATIONS
20LF6‡	20.0	B3-5632-4	69	85	A	4350	CONNECT JUMPER FROM TUBE CAP TO PIN 6 ON OCTAL SOCKET
21GY5‡	20.0	B3-527X-0	30	92	B	9000	DO NOT USE TESTER CAP CONNECTOR. CONNECT CAP TO PIN 2 OF OCTAL SOCKET
21HB5‡	20.0	B3-A72X-0	57	89	A	5600	
21HD5‡	20.0	B3-A79X-0	54	89	A	6000	
21HJ5‡	20.0	B3-A792-X	54	90	A	6500	
21JS6‡	20.0	B3-5632-4	53	88	A	4300	CONNECT JUMPER FROM TUBE CAP TO PIN 6 OF OCTAL SOCKET
21JV6‡	20.0	B3-A732-X	55	91	A	7000	
21JZ6‡	20.0	B3-5632-4	56	91	A	7000	CONNECT A JUMPER FROM CAP TO PIN 6 OF OCTAL SOCKET
21KA6‡	20.0	B3-523X-4	57	89	A	5500	DO NOT USE TESTER CONNECTOR. JUMPER CAP TO PIN 2 OF THE OCTAL SOCKET
21KQ6	20.0	EV-8X39-0	65	87	A	4800	USE ADAPTER SA-8, 1050-168
21LG6‡	20.0	B3-58A4-0	64	86	A	4650	CONNECT CAP OF TUBE TO PIN 6 OF OCTAL SOCKET
21LR8‡	20.0	EV-2673-0	40	87	A	4000	PENT. SECT. USE ADAPTER SA-4, 1050-144. NOTE 3
21LR8	20.0	EV-9801-0	24	62	A	1400	Triode Sect.
Model 6000 A: No Adapter Required.							
21LU8‡	20.0	B3-6489-0	40	87	A	4000	Pent. Sect.
21LU8	20.0	B3-X20A-0	24	62	A	1400	Triode Sect.
21MY8‡	20.0	B3-6489-0	40	87	A	4000	Pent. Setc.
21MY8	20.0	B3-X20A-0	24	62	A	1400	Triode Sect.
22BH3‡	20.0	EV-0209-0	0	87	D	------	MAKE "LINE TEST" AT 1800 ON 3000 SCALE USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000 A: No Adapter Required.							
22BW3‡	25.0	B3-0X07-0	0	89	D	------	
22DE4	25.0	HY-0503-0	0	89	D	------	
22JF6‡	20.0	EV-2X73-8	32	92	B	7800	USE ADAPTER SA-4 1050-144. NOTE 3
Model 6000 A: No Adapter Required.							
22JG6‡	20.0	EV-2973-6	32	92	B	7800	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000 A: No Adapter Required.							
22JR6‡	20.0	EV-2913-6	65	85	A	4200	USE ADAPTER SA-4 1050-144. NOTE 3
Model 6000A: No adapter required.							
22JU6‡	20.0	EV-2X73-8	72	85	A	4200	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000 A: No Adapter Required.							
22KM6‡	20.0	EV-2X73-8	65	89	A	5000	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000 A: No Adapter Required.							
22KV6‡	20.0	EV-2973-6	41	87	B	4800	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000A: No Adapter Required.							
23JS6‡	25.0	B3-5632-4	53	88	A	4300	CONNECT JUMPER FROM TUBE CAP TO PIN 6 OF OCTAL SOCKET. NOTE 3
Model 6000A: No Adapter Required.							
23MB6‡	25.0	B3-5632-4	70	89	A	6400	CONNECT JUMPER FRO TUBE CAP TO PIN 6 ON OCTAL SOCKET
23Z9‡	25.0	B3-8597-0	35	88	A	5000	Pent. Sect.
23Z9	25.0	B3-XA07-0	20	76	A	2200	Triode No. 1
23Z9	25.0	B3-3207-0	30	69	A	1800	Triode No. 2

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.		NOTATIONS
24BF11‡	25.0	B3-8AX9-0	25	88	A	5000	Pentode No. 1
24BF11	25.0	B3-3762-5	19	7	A	600	Pentode No. 2
24GA7‡	25.0	B3-4735-0	58	89	A	4500	Pent. Sect.
24GA7	25.0	B3-0A08-0	0	85	D	------	Diode Sect.
24JE6A‡	25.0	EV-2X73-8	39	92	B	8100	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000 A: No Adapter Required.							
24JZ8‡	25.0	B3-7489-0	32	86	A	4150	Pent. Sect.
24JZ8	25.0	B3-X20A-0	29	60	A	1500	Triode Sect.
24LQ6‡	25.0	EV-2X73-8	39	92	B	8100	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000A: No Adapter Required.							
24LZ6‡	25.0	EV-6X73-8	75	88	A	4500	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000A: No Adapter Required.							
25AV5	25.0	HS-1583-0	42	89	A	5500	
25AX4	25.0	HY-0503-0	0	82	D	------	
25BK5	25.0	EV-3186-0	11	88	A	5000	
25BQ6	25.0	HS-5X48-0	42	89	A	5500	
25C5	25.0	ET-2761-0	20	91	B	7500	
25CA5	25.0	DU-2761-0	20	89	A	5500	
25CD6	25.0	HS-5X83-0	35	90	A	6500	
25CG3‡	25.0	B3-0407-0	0	91	D	------	
25CK3‡	25.0	EV-0209-0	0	86	C	------	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000A: No Adapter Required.							
25CM3‡	25.0	EV-0279-0	0	90	D	------	PLATE TO SCREEN SHORT NORMAL USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000 A: No Adapter Required.							
25CT3	25.0	EV-0209-0	0	94	D	------	OK ABOVE DIODES OK
25DK3	25.0	EV-020X-0	0	86	C	------	
25DN6	25.0	HS-5X83-0	28	93	B	9000	
25EC6	25.0	HS-5X83-0	42	89	A	5500	
25EH5	25.0	ET-2761-0	13	88	A	10000	
25F5	25.0	ET-2761-0	25	85	A	4000	
25F5A	25.0	ET-2761-0	25	86	A	4400	
25H-B25	25.0	EV-2X79-8	50	87	A	4400	USE ADAPTER SA-8, 1050-168
25HX5	25.0	EV-7963-0	50	88	A	5000	USE ADAPTER SA-8, 1050-168
25JQ6	25.0	EV-7139-6	50	85	A	3800	Pent. Sect.
25JQ6	25.0	EV-0609-0	0	70	C	------	Diode Sect.
25JZ8‡	25.0	B3-7489-0	32	86	A	4150	Pent. Sect.
25JZ8	25.0	B3-X20A-0	29	60	A	1500	Triode Sect.
25L6	25.0	HS-5348-1	33	88	A	5200	
25W4	25.0	HY-0503-0	0	88	D	------	
26DQ5	25.0	HS-1X43-0	43	92	A	7800	
26HU5	25.0	HY-1X32-0	70	90	A	7500	
26LW6	25.0	HY-5X32-0	75	88	A	5500	
26LX6‡	25.0	B3-5632-4	70	90	A	7500	CONNECT JUMPER FROM TUBE CAP TO PIN 6 ON OCTAL SOCKET
27LF6‡	25.0	B3-5632-4	69	85	A	4350	CONNECT JUMPER FROM TUBE CAP TO PIN 6 ON OCTAL SOCKET
28D7	25.0	JR-7536-2	13	83	B	3400	Pent. No. 1
28D7	25.0	JR-2436-7	13	83	B	3400	Pent. No. 2
28HA6	25.0	EV-2761-3	10	90	A	6500	
28HD5‡	25.0	B3-A79X-0	54	89	A	6000	

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.		NOTATIONS
29GK6	25.0	EV-2781-3	10	90	A	5750	
29LE6	25.0	EV-8X39-7	65	87	A	4800	USE ADAPTER SA-8 1050-168
30AG11‡	35.0	B3-8709-0	15	87	A	4000	TRIODE NO. 1. MAKE "LINE TEST" AT 1350 ON 3000 SCALE
30AG11	35.0	B3-5604-0	15	87	A	4000	Triode No. 2
30AG11	35.0	B3-0X0A-0	0	76	C	.....	Diode No. 1
30AG11	35.0	B3-0302-0	0	76	C	.....	Diode No. 2
30HJ5‡	25.0	B3-A792-X	54	90	A	6500	
30JZ6‡	25.0	B3-5632-4	56	91	A	7000	CONNECT JUMPER FROM CAP TO PIN 6 OF OCTAL SOCKET
30KD6‡	35.0	B3-5632-4	70	90	A	6400	CONNECT JUMPER FROM TUBE CAP TO PIN6 ON OCTAL SOCKET.
30MB6‡	35.0	B3-5632-4	70	90	A	6400	CONNECT JUMPER FROM TUBE CAP TO PIN 6 ON OCTAL SOCKET
30M-P27	25.0	ET-2761-0	54	84	A	4400	
30R-K47	25.0	EV-090X-0	0	93	D	.....	
31AL10‡	35.0	B3-8457-0	26	90	A	7100	Pent. Sect.
31AL10	35.0	B3-A90X-0	7	85	A	4000	Triode No. 1
31AL10	35.0	B3-3207-0	22	78	A	2900	Triode No. 2
31JS6A‡	35.0	B3-5632-4	53	88	A	4300	CONNECT JUMPER FROM TUBE CAP TO PIN NO. 6 ON OCTAL SOCKET
31LQ6‡	35.0	EV-2X73-8	39	92	B	8100	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000A: No Adapter Required.							
31LR8‡	35.0	EV-2673-0	40	87	A	4000	PENT. SECT. USE ADAPTER SA-4, 1050-144. NOTE 3
31LR8	35.0	EV-9801-0	24	62	A	1400	Triode Sect.
Model 6000A: No Adapter Required.							
31LZ6‡	35.0	EV-6X73-8	75	88	A	4500	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000A: No Adapter Required.							
32ET5	35.0	ET-2761-0	37	86	A	4000	
32GA7‡	35.0	B3-4735-0	58	89	A	4500	Pent. Sect.
32GA7	35.0	B3-0A08-0	0	85	D	.....	Diode Sect.
32HQ7‡	35.0	B3-95A8-0	43	86	B	4500	Pent. Sect.
32HQ7	35.0	B3-0204-0	0	84	C	.....	Diode Sect.
33GT7‡	35.0	B3-A5X8-0	31	91	B	6000	Pent. Sect.
33GT7	35.0	B3-0204-0	0	85	D	.....	Diode Sect.
33GY7‡	35.0	B3-X5A8-0	31	91	B	6000	Pent. Sect.
33GY7	35.0	B3-0204-0	0	85	D	.....	Diode Sect.
33HE7‡	35.0	B3-95A8-0	54	91	A	7000	Pent. Sect.
33HE7	35.0	B3-0204-0	0	89	D	.....	Diode Sect.
33JR6‡	35.0	EV-2913-6	65	85	A	4200	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000 A: No Adapter Required.							
33JV6‡	35.0	B3-A732-X	55	91	A	7000	
34CD3‡	35.0	B3-0X07-0	0	93	D	.....	
34CE3‡	35.0	B3-0407-0	0	86	C	.....	
34CM3‡	35.0	EV-0279-0	0	90	D	.....	PLATE TO SCREEN SHORT NORMAL USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000 A: No Adapter Required.							
34GD5	35.0	ET-2761-0	36	87	A	4500	
34DK3	35.0	EV-020X-0	0	86	C	.....	
35B5	35.0	ET-1562-0	23	87	A	4500	

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.		NOTATIONS
35C5	35.0	ET-2761-0	23	87	A	4500	
35EH5	35.0	ET-2761-0	10	89	A	5000	
35GL6	35.0	ET-2751-0	35	88	A	5300	
35HB8	35.0	EV-9768-0	23	74	A	2100	Pent. Sect.
35HB8	35.0	EV-1302-0	20	63	A	1300	Triode Sect.
35L6	35.0	HS-5348-0	21	87	A	4600	
35LR6‡	35.0	B3-5832-4	85	73	A	2250	CONNECT JUMPER FROM TUBE CAP TO PIN 8 ON OCTAL SOCKET.
35W4	35.0	ET-0507-0	0	88	D	.....	
35Z5	35.0	HS-0508-0	0	88	D	.....	
36AM3	35.0	ET-0507-0	0	88	D	.....	
36KD6‡	35.0	B3-5632-4	70	90	A	7500	CONNECT JUMPER FROM TUBE CAP TO PIN 6 ON OCTAL SOCKET
36LW6	35.0	HY-5X32-0	75	88	A	5500	
36MC6‡	35.0	EV-2X73-8	70	90	A	7500	USE ADAPTER SA-4 1050-144. NOTE 3
Model 6000A: No Adapter Required.							
38HE7‡	50.0	B3-95A8-0	51	91	A	7000	PENT. SECT. MAKE "LINE TEST" AT 1400 ON 2000 SCALE
38HE7	50.0	B3-0204-0	0	86	C	.....	Diode Sect.
38HK7‡	35.0	B3-95A8-0	55	90	A	6000	Pent. Sect.
38HK7	35.0	B3-0204-0	0	87	C	.....	Diode Sect.
40FR5	35.0	ET-2761-0	38	85	A	3900	
40KD6‡	50.0	B3-5632-4	70	90	A	7500	CONNECT JUMPER FROM TUBE CAP TO PIN 6 ON OCTAL SOCKET.
42EC4	50.0	EV-070$-0	0	85	C	.....	USE ADAPTER SA-8, 1050-168
42KN6‡	50.0	B3-5632-4	60	89	A	5000	DO NOT USE TESTER CAP CONNECTOR. JUMPER CAP TO PIN 6 OF OCTAL SOCKET
50BM8	50.0	EV-3672-0	24	86	A	4300	Pent. Sect.
50BM8	50.0	EV-1908-0	11	71	A	1900	Triode Sect.
50C5	50.0	ET-2761-0	20	91	B	7500	
50DC4	50.0	ET-0507-0	0	90	D	.....	
50EH5	50.0	ET-2761-0	13	88	A	10000	
50FE5	50.0	HS-5348-0	30	92	A	8300	
50FK5	50.0	ET-2761-0	20	87	A	4800	
50GY7‡	50.0	B3-X5A8-0	31	91	B	6000	Pent. Sect.
50GY7	50.0	B3-0204-0	0	85	D	.....	Diode Sect.
50HC6	50.0	ET-2751-0	13	88	A	10000	
50HK6	50.0	ET-2751-0	20	91	B	7500	
50HN5	50.0	EV-2793-0	15	93	A	9500	
53HK7‡	50.0	B3-95A8-0	55	90	A	6000	Pent. Sect.
53HK7	50.0	B3-0204-0	0	87	C	.....	Diode Sect.
58HE7‡	50.0	B3-95A8-0	54	91	A	7000	Pent. Sect.
58HE7	50.0	B3-0204-0	0	86	C	.....	Diode Sect.
60FX5	50.0	ET-2761-0	10	90	A	5750	
60HL5	50.0	EV-2793-0	27	91	A	8500	MAKE "LINE TEST" AT 1750 ON 3000 SCALE
KT66	6.3	HS-5348-1	13	90	A	6300	
80	5.0	ER-0300-0	0	22	D	.....	Plate No. 1
80	5.0	ER-0200-0	0	18	D	.....	Plate No. 2
83	5.0	ER-0300-0	0	92	D	.....	Plate No. 1
83	5.0	ER-0200-0	0	90	D	.....	Plate No. 2
KT88	6.3	HS-5348-1	13	88	A	5000	

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.		NOTATIONS
866A	4.3	ER-0X00-0	0	92	D	-----	
884	6.3	HS-5308-0	#	94	F	-----	STRIKES AT ABOUT 8
885	2.5	FR-3204-0	#	94	F	-----	STRIKES AT ABOUT 88
1217	6.3	ET-7562-1	11	59	B	1300	Ampl. Sect.
1217	6.3	ET-1562-7	11	43	B	900	Osc. Sect.
1218A	6.3	ET-6705-0	14	89	A	6000	
1222	6.3	GR-4237-8	17	88	A	5000	
2050	6.3	HS-5308-6	#	94	F	-----	Strikes at about 25
2051	6.3	HS-5308-6	#	94	F	-----	Strikes at about 25
4604	6.3	CX-5X30-0	38	87	A	4500	
5636	6.3	DW-1572-4	13	67	A	1600	Grid No. 1
5636	6.3	DW-4578-1	22	0	B	500	Grid No. 2
5642	1.1	BS-0X00-0	0	0	D	-----	CONNECT FIL. LEADS TO PINS 1 AND 2. OK ABOVE 200 ON 3000 SCALE
5643	6.3	DW-7105-2	#	85	D	-----	Strikes at about 78
5654	6.3	ET-1562-0	24	65	A	1500	
5670	6.3	KR-7608-0	16	86	A	4000	Triode No. 1
5670	6.3	KR-3402-0	16	86	A	4000	Triode No. 2
5672	1.1	DV-4120-0	32	21	B	650	
5675	6.3	HS-3506-0	20	88	A	5000	USE HICKOK ADAPTER SA-9 CODE NO. 1050-121
5676	1.1	ES-3100-0	26	62	A	1400	
5677	1.1	ES-3100-0	38	21	A	650	
5678	1.1	DV-4120-0	12	31	B	750	
5686	6.3	EV-2763-0	11	79	A	2600	
5687	12.6	EV-7906-1	26	91	A	7500	Triode No. 1
5687	12.6	EV-2103-9	26	91	A	7500	Triode No. 2
5696	6.3	ET-1602-5	#	94	F	-----	Strikes at about 25
5702	6.3	DU-7126-5	24	65	A	1500	
5703	6.3	DU-5106-0	26	81	A	3000	
5704	6.3	CT-0104-0	0	79	C	-----	Diode
5718	6.3	DW-1805-7	23	89	A	5500	
5719	6.3	DW-1805-7	17	65	A	1500	
5725	6.3	ET-1562-7	11	48	A	1000	
5726	6.3	ET-0701-6	0	78	C	-----	Diode No. 1
5726	6.3	ET-0205-6	0	78	C	-----	Diode No. 2
5727	6.3	ET-1602-5	#	94	F	-----	Strikes at about 24
5744	6.3	CT-4105-0	16	73	A	2000	
5749	6.3	ET-1567-2	11	72	A	1900	
5750	6.3	ET-7562-1	0	35	B	800	AMPL. SECT. MAKE NO GAS TEST
5750	6.3	ET-1602-7	20	90	A	6500	OSC. SECT. MAKE GAS TEST
5751	12.6	EV-7608-0	12	58	A	1250	Triode No. 1
5751	12.6	EV-2103-0	12	58	A	1250	Triode No. 2
5755	12.6	EV-6807-3	11	31	A	750	Triode No. 1
5755	12.6	EV-3102-6	11	31	A	750	Triode No. 2
5763	6.3	EV-9167-3	11	87	A	4500	
5784	6.3	DU-7126-5	12	75	A	2200	
5814	12.6	EV-7608-0	16	80	A	2775	Triode No. 1
5814	12.6	EV-2103-0	16	80	A	2775	Triode No. 2
5829	6.3	DV-0607-0	0	78	C	-----	Diode No. 1
5829	6.3	DV-0102-0	0	78	C	-----	Diode No. 2
5840	6.3	DW-1574-0	19	78	A	2500	
5842	6.3	DZ-5106-0	19	93	A	8000	
5844	6.3	ET-5207-0	26	81	A	3000	Triode No. 1
5844	6.3	ET-6107-0	26	81	A	3000	Triode No. 2
5847	6.3	DZ-1684-0	11	88	A	5000	
5852	6.3	HS-0508-0	0	0	D	-----	Plate No. 1
5852	6.3	HS-0308-0	0	0	D	-----	Plate No. 2
5876	6.3	HS-3506-0	10	84	A	3600	USE HICKOK ADAPTER SA-9 CODE NO. 1050-121
5881	6.3	HS-5348-1	17	88	A	5000	
5893	6.3	HS-3506-0	10	87	A	4600	USE HICKOK ADAPTER SA-9 CODE NO. 1050-121
5896	6.3	DW-0507-4	0	80	D	-----	Plate No. 1
5896	6.3	DW-0102-4	0	80	D	-----	Plate No. 2
5897	6.3	DW-1805-0	25	84	A	3600	
5899	6.3	DW-1574-0	19	73	A	2000	
5900	6.3	DW-1574-0	19	73	A	2000	
5902	6.3	DW-1572-0	40	86	A	4200	
5903	25.0	DW-0507-4	0	80	D	-----	Plate No. 1
5903	25.0	DW-0102-4	0	80	D	-----	Plate No. 2
5904	25.0	DW-1805-0	36	73	A	2000	
5905	25.0	DW-1572-0	18	70	B	1800	
5906	25.0	DW-1572-0	13	81	A	3000	
5907	25.0	DW-1572-0	15	75	B	2200	
5908	25.0	DW-1572-4	20	69	B	1750	
5915A	6.3	ET-1562-7	11	59	B	1300	Grid No. 1
5915A	6.3	ET-7562-1	11	43	B	900	Grid No. 3
5916	25.0	DW-1572-4	20	67	A	1600	
5930	2.5	ER-3200-0	68	81	A	3000	
5931	5.0	JS-0600-0	0	45	D	-----	Plate No. 1
5931	5.0	JS-0400-0	0	35	D	-----	Plate No. 2
5932	6.3	HS-5348-1	17	88	A	5000	
5933	6.3	FR-3X24-0	25	85	A	3800	
5963	12.6	EV-7608-0	24	75	A	2200	Triode No. 1
5963	12.6	EV-2103-0	24	75	A	2200	Triode No. 2
5964	6.3	ET-5207-6	21	85	A	4000	Triode No. 1
5964	6.3	ET-6107-5	21	85	A	4000	Triode No. 2
5965	12.6	EV-7608-1	16	90	A	6500	Triode No. 1
5965	12.6	EV-2103-6	16	90	A	6500	Triode No. 2
5971	1.1	FT-2100-0	20	65	A	1500	
5975	6.3	EV-3102-0	28	86	A	4000	
5977	6.3	DW-1805-3	32	86	A	4000	
5987	6.3	DW-1205-0	74	71	A	1850	
5995	6.3	ET-0105-0	0	55	D	-----	Leads-1-3-4-5
5998	6.3	HY-4506-2	56	92	A	8000	Triode No. 1
5998	6.3	HY-1203-5	56	92	A	8000	Triode No. 2
6005	6.3	ET-1562-0	11	86	A	4100	
6012	6.3	HS-3501-8	#	94	F	-----	Strikes at about 25
6021	6.3	DW-7805-0	25	78	A	2500	Triode No. 1
6021	6.3	DW-2104-0	25	78	A	2500	Triode No. 2
6028	20.0	ET-1562-0	24	65	A	1500	
6046	25.0	HS-5348-1	33	88	A	5200	
6050	1.1	ES-3100-0	28	60	A	1300	

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.		NOTATIONS
6051	1.1	DV-4120-0	39	0	B	600	
6052	6.3	DW-0507-4	0	80	D	.....	Plate No. 1
6052	6.3	DW-0102-4	0	80	D	.....	Plate No. 2
6053	25.0	DW-0507-4	0	80	D	.....	Plate No. 1
6053	25.0	DW-0102-4	0	80	D	.....	Plate No. 2
6055	25.0	DW-1805-0	36	73	A	2000	
6056	25.0	DW-1572-0	15	75	B	2200	
6058	6.3	ET-0701-6	0	78	C	.....	Diode No. 1
6058	6.3	ET-0205-6	0	78	C	.....	Diode No. 2
6072	12.6	EV-7608-0	18	58	A	1250	Triode No. 1
6072	12.6	EV-2103-0	18	58	A	1250	Triode No. 2
6080	7.5	HY-4506-2	100	83	A	3400	Triode No. 1
6080	7.5	HY-1203-5	100	83	A	3400	Triode No. 2
6082	25.0	HY-4506-2	100	83	A	3400	Triode No. 1
6082	25.0	HY-1203-5	100	83	A	3400	Triode No. 2
6084	6.3	EV-9613-8	18	71	A	1850	
6085	12.6	EV-7608-0	18	80	A	2700	Triode No. 1
6085	12.6	EV-2103-0	18	80	A	2700	Triode No. 2
6086	20.0	EV-2613-9	10	90	A	6500	
6096	6.3	ET-1562-0	24	65	A	1500	
6097	6.3	ET-0701-6	0	78	C	.....	Diode No. 1
6097	6.3	ET-0205-6	0	78	C	.....	Diode No. 2
6098	6.3	GY-7351-0	21	89	A	5400	
6110	6.3	DW-0507-4	0	74	C	.....	Diode No. 1
6110	6.3	DW-0102-4	0	74	C	.....	Diode No. 2
6111	6.3	DW-7805-0	26	86	A	4000	Triode No. 1
6111	6.3	DW-2104-0	26	86	A	4000	Triode No. 2
6112	6.3	DW-7805-0	20	65	A	1500	Triode No. 1
6112	6.3	DW-2104-0	20	65	A	1500	Triode No. 2
6134	6.3	HS-4865-3	11	81	A	3000	
6135	6.3	ET-6107-0	25	75	A	2200	
6136	6.3	ET-1567-2	11	76	A	2300	
6137	6.3	HS-4865-3	12	73	A	2000	
6146	6.3	HS-5X31-8	45	88	A	5000	
6148	6.3	DU-7126-5	24	65	A	1500	
6152	6.3	EV-3102-0	28	86	A	4000	
6159	25.0	HS-5X31-8	45	88	A	5000	
6186	6.3	ET-1562-0	11	78	A	2500	
6189	12.6	EV-7608-0	24	75	A	2200	Triode No. 1
6189	12.6	EV-2103-0	24	75	A	2200	Triode No. 2
6197	6.3	EV-2631-7	11	88	A	5000	
6201	12.6	EV-7608-0	11	82	A	3000	Triode No. 1
6201	12.6	EV-2103-0	11	82	A	3000	Triode No. 2
6202	6.3	ET-0607-1	0	25	D	.....	Plate No. 1
6202	6.3	ET-0107-6	0	25	D	.....	Plate No. 2
6203	6.3	EV-0907-1	0	40	D	.....	Plate No. 1
6203	6.3	EV-0107-9	0	40	D	.....	Plate No. 2
6205	6.3	DW-1572-4	19	78	A	2500	
6206	6.3	DW-1572-4	19	73	A	2000	

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.		NOTATIONS
6211	12.6	EV-7608-2	24	84	A	3600	Triode No. 1
6211	12.6	EV-2103-7	24	84	A	3600	Triode No. 2
6216	6.3	EV-2173-0	20	92	A	9000	
6221	6.3	DW-1805-0	23	84	A	3500	
6222	6.3	DW-1805-0	22	21	A	650	
6223	6.3	DW-1578-0	15	78	A	2500	
6225	6.3	DW-1572-0	11	82	A	3100	
6245	6.3	DU-7126-5	24	65	A	1500	
6247	6.3	DW-2805-0	11	73	A	2000	
6263	6.3	HS-3506-0	18	88	A	5000	USE HICKOK ADAPTER SA-9 CODE NO. 1050-121
6264	6.3	HS-3506-0	10	87	A	4600	USE HICKOK ADAPTER SA-9 CODE NO. 1050-121
6265	6.3	ET-1562-7	12	73	A	2000	
6286	1.4	ES-3100-0	42	62	A	1400	
6293	6.3	HS-5X31-0	24	90	A	6500	
6350	12.6	EV-8607-3	26	87	A	4600	Triode No. 1
6350	12.6	EV-3102-8	26	87	A	4600	Triode No. 2
6384	6.3	GY-7351-0	21	89	A	5400	
6386	6.3	KR-7608-5	24	86	A	4000	Triode No. 1
6386	6.3	KR-3402-5	24	86	A	4000	Triode No. 2
6397	2.5	HR-8360-0	33	72	A	1950	
6414	12.6	EV-7608-0	17	84	A	3500	Triode No. 1
6414	12.6	EV-2103-0	17	84	A	3500	Triode No. 2
6417	12.6	EV-9167-3	11	87	A	4500	
6418	1.4	DV-0204-1	0	0	C	.....	OK ABOVE 300 ON 3000 SCALE
6463	12.6	EV-8607-1	25	88	A	5200	Triode No. 1
6463	12.6	EV-3102-6	25	88	A	5200	Triode No. 2
6485	6.3	ET-1567-2	11	81	A	3000	
6519	1.4	DV-4210-0	0	0	C	.....	OK OVER 850 ON 3000 SCALE
6520	7.5	HY-4506-2	100	79	A	2600	Triode No. 1
6520	7.5	HY-1203-5	100	79	A	2600	Triode No. 2
6526	1.1	DV-4120-0	20	61	B	1250	
6533	6.3	GX-2105-0	20	53	A	1100	
6540	6.3	DU-7126-5	24	65	A	1500	
6611	1.4	DV-0204-1	0	0	C	.....	OK ABOVE 500 ON 3000 SCALE
6612	1.4	DV-0204-1	0	0	C	.....	
6659	OFF	AP-0105-0	0	40	G	.....	Leads =1-5
6660	6.3	ET-1567-2	11	72	A	1900	
6661	6.3	ET-1562-7	12	73	A	2000	
6662	6.3	ET-1562-7	11	72	A	1900	
6663	6.3	ET-0701-6	0	78	C	.....	Diode No. 1
6663	6.3	ET-0205-6	0	78	C	.....	Diode No. 2
6664	6.3	ET-6107-0	11	81	A	3000	
6669	6.3	ET-1562-0	11	86	A	4100	
6676	6.3	ET-1562-7	11	81	A	3000	
6677	6.3	EV-2631-7	11	88	A	5000	
6678	6.3	EV-2637-0	11	73	A	2000	Pent. Sect.
6678	6.3	EV-9108-0	12	90	A	6200	Triode Sect.
6679	12.6	EV-7608-0	11	81	A	3000	Triode No. 1
6679	12.6	EV-2103-0	11	81	A	3000	Triode No. 2
6680	12.6	EV-7608-0	24	75	A	2200	Triode No. 1
6680	12.6	EV-2103-0	24	75	A	2200	Triode No. 2

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.	NOTATIONS
6681	12.6	EV-7608-0	12	58	A 1250	Triode No. 1
6681	12.6	EV-2103-0	12	58	A 1250	Triode No. 2
6688	6.3	EV-2791-8	11	81	A 3000	
6690	6.3	DW-7508-0	22	78	A 2500	Triode No. 1
6690	6.3	DW-2104-0	22	78	A 2500	Triode No. 2
6754	6.3	EV-0907-0	0	80	D ------	Plate No. 1
6754	6.3	EV-0103-0	0	80	D ------	Plate No. 2
6788	6.3	DW-1572-0	13	41	A 900	
6814	6.3	DW-1805-0	24	87	A 4500	
6829	12.6	EV-7608-0	16	90	A 6700	Triode No. 1
6829	12.6	EV-2103-0	16	90	A 6700	Triode No. 2
6832	6.3	DW-7805-0	27	51	A 1050	Triode No. 1
6832	6.3	DW-2104-0	27	51	A 1050	Triode No. 2
6872	6.3	DU-7126-5	14	76	A 2300	
6883	12.6	HS-5X31-8	45	88	A 5000	
6887	6.3	ET-0701-0	0	83	C ------	Diode No. 1
6887	6.3	ET-0205-0	0	83	C ------	Diode No. 2
6889	6.3	GY-7X51-0	21	89	A 5400	
6900	12.6	EV-7906-1	26	91	A 7500	Triode No. 1
6900	12.6	EV-2103-9	26	91	A 7500	Triode No. 2
6919	6.3	ET-0701-6	0	78	C ------	Diode No. 1
6919	6.3	ET-0205-6	0	78	C ------	Diode No. 2
6922	6.3	EV-7608-0	24	89	A 5500	Triode No. 1
6922	6.3	EV-2103-0	24	89	A 5500	Triode No. 2
6928	6.3	ET-1562-0	11	86	A 4100	
6943	6.3	DW-1572-4	14	76	A 2400	
6944	6.3	DW-1572-4	13	76	A 2300	
6945	6.3	DW-1572-0	41	83	A 3200	
6946	6.3	DW-1805-0	24	85	A 3800	
6947	6.3	DW-7805-0	20	79	A 2600	Triode No. 1
6947	6.3	DW-2104-0	20	79	A 2600	Triode No. 2
6948	6.3	DW-7805-0	18	68	A 1650	Triode No. 1
6948	6.3	DW-2104-0	18	68	A 1650	Triode No. 2
6973	6.3	EV-3917-0	10	85	A 4000	
7025	12.6	EV-7608-0	12	58	A 1250	Triode No. 1
7025	12.6	EV-2103-0	12	58	A 1250	Triode No. 2
7027	6.3	HS-5318-0	17	88	A 5000	
7036	6.3	ET-1562-7	11	42	B 900	Grid No. 1
7036	6.3	ET-7562-1	11	35	B 800	Grid No. 3
7044	12.6	EV-7906-0	26	90	A 6000	Triode No. 1
7044	12.6	EV-2103-0	26	90	A 6000	Triode No. 2
7054	12.6	EV-2781-3	11	87	A 4500	
7055	12.6	ET-0701-6	0	78	C ------	Diode No. 1
7055	12.6	ET-0205-6	0	78	C ------	Diode No. 2
7056	12.6	ET-1562-7	11	81	A 3000	
7057	12.6	EV-7608-9	16	87	A 4500	Triode No. 1
7057	12.6	EV-2103-9	16	87	A 4500	Triode No. 2
7058	12.6	EV-7608-0	12	58	A 1250	Triode No. 1
7058	12.6	EV-2103-0	12	58	A 1250	Triode No. 2
7059	12.6	EV-2637-0	11	73	A 2000	Pent. Sect.
7059	12.6	EV-9108-0	12	90	A 6200	Triode Sect.

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.	NOTATIONS
7060	12.6	EV-8679-0	9	84	A 3000	Pent. Sect.
7060	12.6	EV-2103-0	13	83	A 2800	Triode Sect.
7061	12.6	EV-3917-0	11	86	A 4100	
7119	12.6	EV-7906-0	24	94	A 10000	Triode No. 1
7119	12.6	EV-2103-0	24	94	A 10000	Triode No. 2
7137	6.3	ET-6702-0	20	90	A 6000	
7167	12.6	ET-1562-0	11	81	B 3000	
7189	6.3	EV-2793-0	11	90	A 6000	
7199	6.3	EV-7236-0	7	82	A 2500	Pent. Sect.
7199	6.3	EV-9108-0	27	75	A 2100	Triode Sect.
7212	6.3	HS-5X31-8	45	88	A 5000	
7233	6.3	EV-2908-0	0	49	C ------	OK ABOVE DIODES OK
7239	6.3	EV-1X69-7	28	73	A 2100	
7247	12.6	EV-7608-0	12	58	A 1250	Triode No. 1
7247	12.6	EV-2103-0	25	75	A 2200	Triode No. 2
7258	12.6	EV-8679-1	10	85	A 3700	Pent. Sect.
7258	12.6	EV-2173-6	19	87	A 4400	Triode Sect.
7308	6.3	EV-7608-0	24	89	A 5500	Triode No. 1
7308	6.3	EV-2103-0	24	89	A 5500	Triode No. 2
7316	12.6	EV-7608-0	24	75	A 2200	Triode No. 1
7316	12.6	EV-2103-0	24	75	A 2200	Triode No. 2
7355	6.3	HS-6385-0	12	91	A 7600	
7357	25.0	HS-5X31-8	45	88	A 5000	
7358	6.3	HS-5X31-8	23	91	A 7000	
7360	6.3	EV-3621-9	18	50	A 1000	CONNECT PIN 1 TO PIN AND PIN 6 TO PIN 7 ON LOCTAL SOCKET
7370	20.0	FY-7906-0	26	91	A 7500	Triode No. 1
7370	20.0	JU-2103-0	26	91	A 7500	Triode No. 2
7408	6.3	HS-5348-1	13	86	A 4100	
7543	6.3	ET-1567-2	11	76	A 2300	
7551	12.6	EV-2631-7	17	90	A 6000	
7558	6.3	EV-2631-7	17	90	A 6000	
7581	6.3	HS-5348-0	17	88	A 6000	
7586‡	6.3	DR-4208-0	28	78	A 2500	USE ADAPTER SA-3, 1050-127. NOTE 3
Model 6000 A:						
7586	6.3	13-4208-0	28	78	A 2500	
7587‡	6.3	DR-4X28-0	11	85	B 3800	USE ADAPTER SA-3, 1050-127. NOTE 3
Model 6000 A:						
7587	6.3	13-4528-0	11	85	B 3800	
"Do not use tester cap connection. Jumper plate cap to Pin 5 octal socket."						
7591	6.3	HS-6345-0	10	89	A 5100	
7683	6.3	EV-1382-0	10	50	A 1250	
7687	6.3	EV-2637-0	10	82	A 3200	Pent. Sect.
7687	6.3	EV-9108-0	29	79	A 2100	Triode Sect.
7695	50.0	EV-6917-0	30	94	A 9000	
7701	12.6	EV-2691-0	10	83	A 3300	
7716	12.6	EV-7986-0	10	87	A 4500	Pent. Sect.
7716	12.6	EV-2301-0	10	69	A 1700	Triode Sect.
7717	6.3	ET-1562-0	11	81	B 3000	
7719	12.6	EV-2103-0	29	84	A 3500	

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.		NOTATIONS
7724	12.6	EV-8907-0	10	15	A	600	Triode Sect.
7724	12.6	EV-0601-0	0	80	C	------	Diode No. 1
7724	12.6	EV-0203-0	0	80	C	------	Diode No. 2
7728	12.6	EV-7608-0	11	81	A	3000	Triode No. 1
7728	12.6	EV-2103-0	11	81	A	3000	Triode No. 2
7729	12.6	EV-7608-0	12	58	A	1250	Triode No. 1
7729	12.6	EV-2103-0	12	58	A	1250	Triode No. 2
7730	12.6	EV-7608-0	24	75	A	2200	Triode No. 1
7730	12.6	EV-2103-0	24	75	A	2200	Triode No. 2
7731	6.3	EV-2637-0	11	73	A	2000	Pent. Sect.
7731	6.3	EV-9108-0	12	90	A	6200	Triode Sect.
7732	6.3	ET-1562-7	11	81	A	3000	
7733	12.6	EV-2781-3	11	87	A	4500	
7734	6.3	EV-8917-0	14	72	A	1850	Pent. Sect.
7734	6.3	EV-3602-0	64	86	A	4700	Triode Sect.
7737	6.3	EV-2791-8	11	81	A	3000	
7738	6.3	ET-2105-0	13	89	A	5500	
7754	6.3	EV-6917-0	30	94	A	9000	
7757	6.3	DV-6X78-0	11	86	A	4100	
7759	25.0	DW-7805-0	25	78	A	2500	Triode No. 1
7759	25.0	DW-2104-0	25	78	A	2500	Triode No. 2
7760	25.0	DW-7805-0	36	73	A	2000	Triode No. 1
7760	25.0	DW-2104-0	36	73	A	2000	Triode No. 2
7761	25.0	DW-1572-0	15	87	A	4700	
7762	25.0	DW-1572-0	40	86	A	4200	
7802	6.3	HY-4506-2	45	93	A	9500	Triode No. 1
7802	6.3	HY-1203-5	45	93	A	9500	Triode No. 2
7803	6.3	EV-7608-0	22	91	A	7000	Triode No. 1
7803	6.3	EV-2103-0	22	91	A	7000	Triode No. 2
7861	12.6	KR-7608-0	17	88	A	5000	Triode No. 1
7861	12.6	KR-3402-0	17	88	A	5000	Triode No. 2
7867	6.3	HS-5X83-0	23	93	B	9000	
7868‡	6.3	EV-2973-0	18	89	A	5200	USE ADAPTER SA-4, 1050-144. NOTE 3
Model 6000 A:	No Adapter Required.						
7889	25.0	DW-7805-0	20	65	A	1500	Triode No. 1
7889	25.0	DW-2104-0	20	65	A	1500	Triode No. 2
7895‡	6.3	DR-4208-0	22	82	A	3200	USE ADAPTER SA-3, 1050-127. NOTE 3.
Model 6000 A:							
7895	6.3	13-4208-0	22	82	A	3200	
7898	6.3	EV-7608-0	11	86	A	4000	Triode No. 1
7898	6.3	EV-2103-0	11	86	A	4000	Triode No. 2
7905	6.3	KR-2680-7	10	88	A	4650	
7984‡	12.6	B3-X3A9-0	42	87	A	4050	
7995	6.3	ER-3782-6	13	82	A	3100	
8032	12.6	HS-5X31-8	45	88	A	5000	
8056‡	6.3	DR-0208-4	0	68	C	------	OK ABOVE 1300 ON 3000 SCALE USE ADAPTER SA-3, 1050-127. NOTE 3
Model 6000 A:							
8056	6.3	13-0208-4	0	68	C	------	OK ABOVE 1300 ON 3000 SCALE

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.		NOTATIONS
8058‡	6.3	DR-5X02-0	19	85	A	3800	JUMPER SHELL TO PIN 5 OF LOCTAL SOCKET USE ADAPTER SA-3, 1050-127. NOTE 3
Model 6000 A:							
8058	6.3	13-5102-0	19	85	A	3800	
"Do not use tester cap connector. Jumper tube cap to Pin 1 of octal socket. Jumper shell to Pin 5 of novar socket."							
8064	25.0	DW-1578-0	15	75	A	2150	
8068	6.3	HS-5X83-0	15	90	A	7000	
8077	12.6	EV-2781-3	11	87	A	4500	
8084	12.6	DU-1562-7	18	81	A	3000	
8096	6.3	GX-2105-0	20	53	A	1100	
8102	12.6	EV-9678-0	11	81	A	3000	Pent. Sect.
8102	12.6	EV-3102-0	21	85	A	3900	Triode Sect.
8106	12.6	EV-7189-0	16	87	A	4450	
8113	6.3	ET-1567-0	22	82	A	2600	
8136	6.3	ET-1562-7	12	83	A	3300	
8149‡	12.6	B3-X789-0	44	88	A	4500	
8150‡	12.6	B3-X386-0	44	88	A	4500	CAP-P. JUMPER FROM PIN 3 TO CAP
8156‡	12.6	B3-X376-0	25	90	A	5000	
8185	6.3	JR-2306-0	25	87	A	4300	
8186	25.0	JR-2306-0	25	87	A	4300	
8203‡	6.3	DR-4208-0	29	78	A	2400	USE ADAPTER SA-3, 1050-127. NOTE 3
Model 6000 A:							
8203	6.3	13-4208-0	29	78	A	2400	
8236	6.3	HS-1X43-0	43	92	A	7800	
8298	6.3	HS-5X31-8	23	90	A	8000	
8327	6.3	EV-2793-0	23	92	A	5500	
8334	6.3	ET-6705-0	14	89	A	6000	
8393‡	12.6	DR-4208-0	27	85	A	3700	USE ADAPTER SA-3, 1050-127. NOTE 3
Model 6000 A:							
8393	12.6	13-4208-0	27	85	A	3700	
8417	6.3	HS-5348-0	10	93	A	10000	
8425	6.3	ET-1567-2	10	80	A	2900	
8426	12.6	ET-1567-2	10	80	A	2900	
8431	12.6	EV-7608-0	18	93	A	5500	Triode No. 1
8431	12.6	EV-2103-0	18	93	A	5500	Triode No. 2
8445	6.3	EV-2637-0	10	84	A	3500	Pent. Sect.
8445	6.3	EV-9108-0	20	84	A	3500	Triode Sect.
8446	6.3	EV-9678-0	10	82	A	3000	Pent. Sect.
8446	6.3	EV-1203-0	14	87	A	4000	Triode Sect.
8489	6.3	EV-8679-0	10	84	A	3600	Pent. Sect.
8489	6.3	EV-2103-0	20	85	A	3800	Triode Sect.
8532	6.3	ET-1702-0	20	90	A	6000	
8552	12.6	HS-5X31-8	23	91	A	7000	
8628‡	6.3	BT-4208-0	15	70	A	1900	USE ADAPTER SA-3, 1050-127. NOTE 3
Model 6000 A:							
8628	6.3	13-4208-0	15	70	A	1900	