

PM 2

| | Hersteller | | Ua | Ia | Ug | S | Ri | Ra | Raa | RK | μ | P | Pa | Socket |
|---------|------------|---------------|-----|-----|-----|-----|-----|-----|-----|----|-------|-----|-----|--------|
| PM 2 | Mullard | Triode | 150 | 7 | -12 | 1,7 | 5k | | | | | | | 1 |
| PM 2 A | Mullard | Triode | 135 | 6 | -6 | 2 | 6k | 10k | | | 10 | | 0,2 | 1 |
| PM 2 B | Mullard | Doppel Triode | 120 | 7 | -3 | 2 | 4k | | 10k | | 9 | 2 | | 2 |
| PM 2 BA | Mullard | Doppel Triode | 120 | 2 | -5 | | | | 14k | | | | | 2 |
| PM 2 DL | Mullard | Triode | 125 | 2,1 | -4 | 1,5 | 12k | | | | 18 | | | 1 |
| PM 2 DT | Mullard | Triode | 150 | 3 | -4 | 1,3 | 13k | | | | 17 | 0,9 | | |
| PM 2 DX | Mullard | Triode | 135 | 2,2 | -4 | 1 | 18k | | | | 18 | | | 1 |
| PM 2 HL | Mullard | Triode | 135 | 2,2 | -4 | 1 | 18k | | | | 18 | | | 1 |

| Legende | | |
|---------|---|---------------------------------|
| Ua | = | Anodenspannung (Volt) |
| Ia | = | Anodenstrom (mA) |
| Ug | = | Gitterspannung (Volt) |
| S | = | Steilheit |
| Ri | = | Innenwiderstand (Ω) |
| Ra | = | äußerer Widerstand (Ω) |
| Raa | = | Ra: Anode zu Anode (Ω) |
| RK | = | Katodenwiderstand (Ω) |
| μ | = | Verstärkungsfaktor |
| P | = | Ausgangsleistung (Watt) |
| Pa | = | Anodenleistung (Watt) |

