


$U_f = 6,3V$ (Sk126)
7,5

$U_{g1} = -7V$ (Sk140)
7,5

$U_{g2} = 250V$ (Sk125)
300

$U_a = 250V$ (Sk125)
300

No 84



ECL86 (P)

6HG8
6DW8

Fassung Nr. 11 (Noval), EmF = 1,43

EOL
 $I_a < 22mA$
 $S < 6mA/V$
 $I_{g1} > 1\mu A$

Emission in %: U_{g1} so einstellen, dass $I_a = 36mA$, U_{g1} und S messen. $Em[\%] = -U_{g1} \cdot S \cdot EmF$

U_{fk}
100V

● U_{g1}

U_{g2} ●

● U_a

● U_b 350 V~ ●

AOE 2023 $I_a = 36 mA$ (Sk72)

$I_{g2} = 6,0mA$ (Sk120)

$I_{g1} < 1\mu A$ (Sk50)

$S = 10mA/V$