


Uf = 14V (Sk140)
15

Ug1 = -1,7V (Sk85)
3

Ua = 253V (Sk115)
300

PCL86 (T) 14GW8



Fassung Nr. 11 (Noval), EmF = 36,8

EOL
Ia < 1,0mA
S < 1,0mA/V
Ig1 > 1,0µA

Ug1

Ua

Emission in %: Ug1 so einstellen, dass Ia = 1,2mA, Ug1 und S messen. Em[%] = -Ug1*S*EmF

Ufk
100V

Ub 350 V~

AOE 2023 Ia³ = 1,2mA (Sk60)

Ig1³ < 1µA (Sk50)

S³ = 1,6mA/V (Sk80)